THE
INSTITUTION
OF
CIVIL ENGINEERS.

SESSION 1906-1907.—PART II.

SECT. I.—MINUTES OF PROCEEDINGS.

18 December, 1906.

Sir ALEXANDER B. W. KENNEDY, LL.D., F.R.S., President,
in the Chair.

(*Paper No. 3589.*)

“Mechanical Considerations in the Design of
High-Tension Switch-Gear.”

By HENRY WILLIAM EDWARD LE FANU, M. Inst. C.E.

CO-ORDINATELY with the increase in the output and pressure of electrical machinery during the last 15 years, a remarkable development has taken place in the general design and arrangement of the high-tension switch-gear which controls such machinery. The result of these years of experience has been to establish several distinct types of gear, each of which has, under certain conditions, proved fully satisfactory in practice. The tendency of the mechanical design of modern switch-gear has been to confine accidents, resulting from defective insulation, short-circuits, mistakes in manipulation, etc., within the smallest possible limits, and so to prevent the consequences of such accidents from spreading to adjoining apparatus and causing serious breakdowns.

PARTITIONING OF HIGH-PRESSURE APPARATUS.

The first step in this direction was taken by Mr. S. Z. de Ferranti, M. Inst. C.E., who recognized at an early date the necessity of partitioning all high-tension apparatus, and of thereby preventing accidental contact between the various parts under tension. He further appreciated the advisability of a thoroughly systematic arrangement of all apparatus, connections, bus-bars, etc. The Ferranti cellular switchboard was for many years the only example embodying these principles.

In earlier switchboards, in order to avoid arcking in the air-break

[THE INST. C.E. VOL. CLXVIII.]

B

switches, the different poles were protected by plates of asbestos, slate, or marble. Similarly, the bus-bars were separated throughout by slabs of slate or marble, and were supported upon double porcelain insulators mounted on a marble base. In order to separate more effectually the apparatus belonging to the various units or panels, and to be able to isolate them for repairs in case of breakdowns, heavy marble or slate slabs were inserted between the adjoining panels, or masonry walls built into the framework of the switch-board were employed. Any metallic framework, being liable to cause dead short-circuits in case of breakage of insulators, has been dispensed with altogether in more recent designs.

The adoption of the oil-switch, instead of the unreliable air-break type, marks another step in the successful control of large amounts of energy under the most severe conditions of practice. The old safety device—the fuse—was also replaced by the circuit-breaker,¹ an apparatus designed to operate automatically on overloads in the case of feeder-circuits, and on reverse currents in generator-circuits.

With switch-gear of large capacity the whole system is protected, and, whenever possible, apparatus and cabling of different polarity are separated by masonry walls, or by heavy barriers of concrete, slate, or marble. The earlier practice of combining on the same framework all switch-gear, high- and low-tension, was soon given up, and the necessary separation of these parts brought about the introduction of remote control for the high-pressure section.

As the capacity of power-stations and the pressure employed increased, methods of carrying out the foregoing principle developed. Certainty of operation and the safety of the operator had to be provided for; but it was also essential that all parts of the gear should be easily accessible for inspection and repairs, and that continuity of supply, in case of breakdown of any one machine, apparatus, or feeder, should be adequately assured.²

The object of this Paper is to describe, from a mechanical point of view, examples of high-tension switch-gear, which have successfully borne the test of practice. For simplicity, only three-phase gear has been considered, but the same principles apply, with slight modifications, to single-phase or two-phase installations. As the

¹ In his "Notes on Three-Phase Switch-Gear," *Engineering*, vol. lxxvi (1903), p. 409, Mr. A. C. Eborall treated very fully the question of the replacement of fuses by oil circuit-breakers.

² Mr. E. W. Rice, Jun., in 1901 laid down several fundamental rules concerning the protection of apparatus in fire-proof cells, the arrangement of circuits, etc., which form practically the basis of all modern high-pressure switch-gear. See his Paper "The Control of High-Potential Systems of Large Power." *Transactions of the American Institute of Electrical Engineers*, vol. xviii, p. 407.

development of the various methods of controlling the energy in power-stations of large capacity is best shown in contrast with the gear for smaller plants, a short account of the latter will first be given.

EXAMPLES OF SWITCH-GEAR FOR STATIONS OF SMALL CAPACITY.

To fulfil the primary condition—the separation of high- and low-tension apparatus—all this switch-gear was designed for remote control, either mechanical or electrical. Figs. 1, Plate 1, are the section and plan of a switchboard for the distribution of energy, for lighting and power, in a colliery. There are two three-phase alternators, each of 300 kilowatts, 3,000 volts, with direct-coupled exciters; several outgoing high-tension feeders; and one step-down transformer for feeding the local power-circuits at 500 volts. The local lighting-circuits are fed from the exciters.

The high-tension compartments are placed against the wall of the building, the operating-panels being mounted on a gallery about 3 feet above the machine-room floor, and about 4 feet in front of the masonry compartments, leaving a free passage between. The girders of the switchboard-gallery form one structure with the framework of the operating-panels. The flooring of the gallery is either of chequered plating or of wood lined on the lower side with asbestos, or other fire-resisting material.

The high-tension cables coming from the alternators enter the compartments at the bottom, are connected to the various instrument- and relay-transformers, the circuit-breakers, and panel section-switches, and are finally joined to the bus-bars, which are placed above the passage between the compartments and the operating-board. For the feeders the reverse order must be taken. In order to simplify the arrangement of apparatus and wiring, there are nine low-tension panels, so arranged as to give complete separation according to the nature of the current controlled by them. Facing the board, these low-tension panels are disposed from left to right thus:—

(a) Continuous current. One panel for the local lighting-circuits one panel for the two direct-driven exciters.

(b) Low-tension alternating current. Two panels for the two alternators, two for the four high-tension feeders.

(c) Medium-tension alternating current. One panel for the low-tension side of the power-transformer, and two for four feeders branched from the transformer.

(d) A small panel mounted on a swivel bracket contains the synchronizing-instruments.

Eight high-tension compartments are necessary:—Two for the

alternators, four for the feeders, one for the synchronizing-transformer and the multiple-way switch for the electrostatic ground-detector, and one for lightning-arresters, since several of the feeders are overhead.

In order to reduce the width of the operating-panels to the minimum just necessary for all the low-tension gear, it was not possible to keep the high-pressure compartments in line with the corresponding low-tension panels without undue cramping of the high-tension apparatus, or without augmenting unnecessarily the size of the operating-panels.

The compartments were therefore displaced relatively to the panels, the only difficulty encountered being the disposal of the circuit-breaker driving-rods. The complication entailed was, however, more than outweighed by the economy gained through the reduction in length of the operating-panels.

The high-tension compartments are formed by brick walls coated with cement, having a total thickness of about $5\frac{1}{2}$ inches, and are covered in at the top by cement slabs 2 inches thick (Figs. 1, Plate 1). Each compartment is subdivided into three cells by similar barriers. These smaller cells serve for the reception of:—

- (a) The cable-dividing boxes and the instrument-transformers with their fuses.
- (b) The circuit-breakers.
- (c) The panel section-switches.

The high-pressure bus-bars are doubly insulated by heavy porcelain insulators, and are separated by slate plates, thereby preventing risk of accidental short-circuits.

The driving-rods of the switches are mounted below the bus-bars, and the low-tension wiring is carried under the switchboard-gallery to the operating-panels. As shown in Figs. 1, the various field-regulating and discharge resistances, and the low-tension apparatus for the excitation-, lighting-, and power-circuits, are placed at the back of the low-pressure board. As in mining installations it is not usual to allow any live parts to be mounted on the front of the board, a special type of switch, with contacts behind the panels, was provided.

The high-tension circuit-breakers are designed on the “free-handle” principle, rendering it impossible to keep the switch closed on a short-circuit. Two breaks are provided per pole, and the opening of the switch is assisted by a powerful spring. The oil-tank into which the contacts plunge is divided by insulating partitions into three compartments, to prevent arcking from pole to pole. All contacts and terminals are carried on heavy corrugated porcelain insulators.

A design of switch-gear for a station of 3,000 kilowatts capacity, with machine units of 750 kilowatts, is shown in section in *Fig. 2*.

Fig. 2.

SECTION THROUGH HIGH-PRESSURE SWITCHBOARD (6,500 VOLTS, 750-KILOWATT UNITS).

The high-tension gear is underneath the switchboard-gallery (or in the basement), on either side of a strong brick wall. The bus-bars are mounted in separate horizontal concrete ducts, and with the section-switches above are very accessible. The connections from the section-switches to the bus-bars are laid in vertical recesses cut in the brick wall.

As the number of units—alternators and feeders—was large in this case, and as only one series of bus-bars was used, the feeder-panels and compartments were arranged symmetrically on either side of those of the machines, and the bars were divided by switches into four sections. Thus, in case of a breakdown on any section of the bars, only one-half of the feeders would be put out of service. Each sub-station is fed by at least two feeders, and continuity of supply is assured by arranging that no sub-station is supplied by feeders branching from the same section of bus-bars.

The field-regulating resistances are placed against the wall of the building, behind the operating-panels, leaving the space at the back of the panels free for the low-tension connections and smaller apparatus. The secondary wiring between the compartments and the low-tension board, as well as the exciter-cables, are brought up against the wall of the building and laid between double flooring behind the operating-panels. Where possible it is better to fix this wiring directly underneath the switchboard-platform.

HIGH-PRESSURE CIRCUIT-BREAKERS.

The character of a design for switch-gear is practically determined by the circuit-breakers. In the equipment just described the normal rating of the circuit-breakers is 800–1,000 kilowatts, at 6,500 volts. For larger capacities a radically different type becomes essential. The length and quickness of break must be increased to ensure opening the circuits with certainty under the most unfavourable conditions. Better protection of the different poles from each other, as well as from the metallic supporting frame, must be provided for.

The circuit-breaker shown in Figs. 3, Plate 1, has six breaks and is rated at 3,000 kilowatts, 10,000 volts. Four steel columns rising from a cast-iron bed-plate support a strong cast-iron frame of U section, on which the driving mechanism is mounted, and to which, on the lower side, the main contacts are fixed. A stout plate of soapstone is interposed between these contacts and the frame. The fixed contacts, which are immersed in separate oil-tanks placed below the frame, are held in heavy porcelain insulators of the corrugated

type and are bridged by movable gun-metal knives carried by three vertical rods, from which they are insulated by porcelain and paper bushings. These rods, carried by a cast-steel cross-bar of rectangular section, are suspended by links and connected by levers to a horizontal spindle, so that a straight-line motion is imparted to the system of movable contacts. In order to leave the incoming and outgoing cables completely free, the operating- and tripping- magnets are placed on one end of the frame. The operating-magnet is mounted on four steel columns, threaded at their ends, so that the height of the magnet may be adjusted. The tripping-magnet is fixed on a special support bolted to the frame.

As it is of importance to be able readily to inspect the contacts, the three oil-tanks rest on a cast-steel base supported on two threaded steel columns, and, by means of a reversible ratchet fixed underneath the base-plate, they can be lowered or raised. The tanks, which are held in place by pressing them up against the circuit-breaker frame with the ratchet mechanism, are made of sheet metal and are lined with wood or an insulating and non-inflammable compound, and an oil-level gauge and drain-cock are fixed to each of them. To prevent contact between the phases, in case of a breakdown on one pole, heavy slabs of soapstone or slate are placed between the tanks and between these and the switch-frame. The vertical plates fit into grooves and can be moved out of the framework should occasion arise. The horizontal slabs are fixed to the frame.

The contacts of the circuit-breaker are of the spring-wedge type and of a heavy design necessary for mechanical strength. To avoid arcking between the main contacts, the circuit is broken by parallel auxiliary contacts after the main contacts have already opened.

The porcelain insulators carrying the copper rods to which the contacts and terminals are fixed are designed with large surfaces to prevent leakage. Should these insulators break, arcking to the frame is further prevented by a sheathing of "micanite" and paper placed around the rods.

The circuit-breaker is operated in the following manner:—For closing it, the driving-magnet is energized and its core lifts, by means of a connecting link and toggle-joint, an arm which actuates the horizontal spindle, and thus raises the movable contacts into the closed position. To prevent the core of the operating-magnet from falling when the current is taken off, one end of the link forming the toggle-joint engages a spring catch. The whole weight of the mechanism is taken up by the toggle-joint, and only a small pressure remains upon the catch. For opening the switch the tripping-coil is magnetized, whereupon its core, as it lifts, transmits through a lever

and tripping-rod a hard blow upon the interlocking catch. This blow disengages from the driving mechanism the whole system of movable contacts, which, in falling, opens the circuit. As the weight of the movable parts is considerable, the break is quick, and it has not been found necessary to aid the action of gravity by springs. In case the tripping-coils should fail to act, an auxiliary mechanical release catch is fitted to the switch. It is undesirable that the attendant should be obliged to enter the high-pressure room to manipulate this catch, hence it should be operated by a steel wire or cable from the operating-board or columns. This reserve release is of great importance, as the failure of a switch to open may be attended with the gravest results.¹

The upward movement of the mechanism is limited by a stop arranged on the toggle-joint, and its fall is taken up by steel springs. On opening the switch the driving mechanism and magnet-core remain suspended until the catch holding the toggle-joint is released by one end of the falling cross-bar.

As will be seen from the foregoing description, the design of the operating mechanism is based on the "free-handle" principle, for the mechanism of the circuit-breaker proper is quite independent of the driving-gear. There is, in fact, no connection between the two, save the interlocking catch, which, when the switch is closed on a short circuit, is released as soon as the auxiliary contacts close the circuit.

The current taken by the operating-magnet is about 46 amperes at 45 volts (continuous current), and by the tripping-magnet, about 2 amperes at 45 volts (continuous current). As the magnet-coils are in circuit only for a short time during each operation, they may be wound for a high current-density. For security under these conditions it is necessary to make it impossible for the operator to keep the current on the magnet and so burn out the winding, as the damage thus caused might escape detection until the switch had again to be closed, when failure to operate would cause considerable inconvenience. To avoid this, the control-switch is designed in such a manner that the operator has only to turn the handle through an angle slightly larger than 180 degrees, thereby compressing a spring, which during the second half revolution completes the movement of the controller-barrel independently of the operating-handle. The time during which the current must flow in order to ensure the closing of the circuit-breaker is regulated by a dashpot. A simpler arrangement, adequate in many cases, consists of a switch provided with a spring, so

¹ In large power-stations, where the group switches afford additional security this auxiliary release is unnecessary.

that when the operator releases the handle the control-switch opens.

In most cases it is advantageous, from considerations of space and economy, to replace the bed-plate and supporting columns of these switches by a masonry structure.

This method has been employed for years with great success by the General Electric, British Thomson-Houston, and Westinghouse companies. Each phase is built into a separate cubicle, accessible from the front by removing a sheet-metal door. The terminals are completely separated from the mechanism, and, with the doors of the cubicles closed, are inaccessible from outside. The switch consists of two entirely separated parts, the electrical mechanism, which is completely enclosed in the masonry structure, and the operating mechanism, which is placed above the cells and is easily accessible (Figs. 15, Plate 2). The circuit-breakers built by the Thomson-Houston Company are controlled by a small motor, whereas the Westinghouse Company employs solenoid control.

A novel feature in the design of such apparatus has been introduced by Messrs. Ferranti, who avoid the use of all intermediary levers and shafts in the driving-mechanism. The great difficulty in solenoid control is to obtain a long stroke of the core combined with the necessary lifting-power. Messrs. Ferranti overcome the difficulty by dividing the solenoid into two portions, an upper and a lower, each provided with a separate plunger (Figs. 4, Plate 1). The lower plunger is rigidly attached to the moving contact-system. The upper plunger is concentric with, but not directly attached to, a rod which forms virtually a prolongation of the lower plunger. The upper end of this rod is provided with a collar, which rests upon the top surface of the upper plunger when the switch is in the open position. Both solenoids are energized together, the first half of the stroke being effected mainly by the upper plunger being drawn within its solenoid to its full extent, and carrying the switch mechanism with it, by virtue of the collar. By this time the lower plunger has been brought into a favourable position to be acted upon by the lower solenoid, and the second half of the stroke is completed. By this device a very powerful long-pull electromagnet is obtained, giving a stroke of 10 inches with a minimum pull of 180 lbs., and a maximum pull at the end of the stroke of 400 lbs.

This switch is held in the closed position by the usual toggle-joint, thus preventing it from opening in consequence of vibration. There are two other distinguishing features about the Ferranti circuit-breaker which are of great importance in respect of reliability in opening circuit. The first consists in the employment of insulating

slabs surrounding the rods to which the moving contacts are attached. These slabs slide down into the tanks, each tank being thus divided into two separate compartments for the purpose of minimizing the risk of under-oil arcking. The second and more important feature has reference to the oil-space of about $\frac{3}{8}$ inch, between the walls of the tank and the insulating lining. When the circuit is broken under oil, the arc which forms drives the oil from the immediate neighbourhood of the contacts, thus considerably decreasing for the time the dielectric resistance between each pole and the tank or earth. The layer of oil, however, between the tank lining and case, remains quite undisturbed, and maintains the dielectric resistance during the break.

It is desirable, in order to avoid difficulties of erection when masonry support is used, that all apparatus, such as circuit-breakers, section-switches, rheostats, etc., should be, as far as possible, self-contained.

REMOTE CONTROL FOR HIGH-PRESSURE CIRCUIT-BREAKERS.

Remote control for the circuit-breakers may be electrical or mechanical, or a combination of both systems. The choice depends to a certain degree on the local conditions. Where it is possible to establish a short and direct drive, it seems wisest to employ mechanical control, and especially for feeder circuit-breakers which need not be often manipulated. Manual control has this advantage over electrical, that no auxiliary source of energy is required and there are no troublesome control-switches and connecting cables. Where electrical control is adopted, provision should be made to close the circuit-breakers mechanically by an auxiliary lever, in order to avoid the inconvenience of leaving one of the generating-units or feeders idle while in search of a fault in the control-circuits or during repairs on the operating-magnet or motor of the corresponding switch. Electrical control becomes, of course, imperative where space is limited, and where a large number of circuits have to be dealt with.

The various parts constituting the mechanical driving-gear should be of strong and simple construction. Contrary to the ordinary practice with small circuit-breakers, in which the driving mechanism is fixed directly to the steel framework of the operating-panels, in the case of large circuit-breakers the heavy cast-iron supports, with their levers, should be placed in front of the corresponding panels, and bolted to the floor-girders. This arrangement prevents the communication of vibrations to the operating-panels when manipulating such heavy switches. The main driving-lever is provided with a

smaller auxiliary lever, which engages a catch in both the open and the closed position. The main lever is thus securely held in position and is prevented from being displaced through inadvertence.

When a circuit-breaker which is designed on the free-handle principle opens automatically, or when it is opened by closing the tripping-coil circuit, the driving mechanism remains in the closed position, and has to be brought back by hand, in order to be reset for a fresh operation. This independence of the driving mechanism from the movable part of the circuit-breaker proper is very important for the rapid opening of the switch, as no heavy pieces have to be put in motion save those of the switch itself. In this respect, therefore, there is nothing to choose between electrical and mechanical control.

With remote control, an optical indicator, mounted on the front of the operating-panels, becomes necessary for each circuit-breaker. Such an indicator consists of two differently-coloured lamps, of which one or the other should be always alight, in order that the operator may tell by a glance at the board which of the circuit-breakers is closed and which open. It is useful also to provide an alarm-bell, which rings when one of the generator- or feeder-switches opens automatically.

A small "contactor" is coupled to the movable part of the circuit-breaker. Its function is two-fold. It serves to make and break automatically the circuits of the signal-lamps and alarm-bell, and to open the discriminating and overload relay-circuits. These relays are delicate instruments, and, if they are not provided with carbon contacts, it is necessary, on account of the small arcs which occur between their contacts on opening, to break circuit with a contactor. The contactor will be seen on the right of the circuit-breaker in Fig. 3, Plate 1. *Fig. 5* is a general diagram of connections of electrically-operated circuit-breakers.¹

¹ It is not within the scope of this Paper to enter into a description of the relays used in connection with these circuit-breakers, a subject which has been fully discussed in a Paper by Mr. L. Andrews, "High Tension Switch-Gear," *Journal of the Institution of Electrical Engineers*, vol. xxxiv (1905), p. 438.

With regard to the type of relay to be used, Mr. Andrews sums up in the following rule:—

"Where current is fed into bus-bars from a number of sources of supply connected in parallel, discriminating cut-outs only should be used. Where current leaves bus-bars to supply a number of feeders, transformers, motors, or distributors, excess-current cut-outs only should be used."

Although Mr. Andrews pointed out this simple and really self-evident maxim many years ago, the importance of the choice in the protection of machines and feeders has not as yet been universally realized, and it is not unusual to find the time-honoured fuse, or a combination of reverse and overload relays, doing service

Fig. 5.

CONNECTIONS FOR ELECTRICALLY-OPERATED THREE-POLE OIL CIRCUIT-BREAKER
(TWO BREAKS PER POLE).

(The connections are shown for the open position of the switch.)

in alternator-circuits, or even overload relays without time-limit attachment in the machine, and fuses in the feeder-circuits.

There is one other point with respect to these protective devices which is often neglected on account of the higher initial cost of the apparatus. Three-phase circuits are usually considered amply protected by the insertion of protective devices in two phases only. Under ordinary circumstances this may, of course, suffice, but account should be taken of the fact that a relay or its transformer may break down, or some fault develop in the connections between the circuit-breaker and the relay or between the latter and its transformer, thus rendering one pole of the relay inoperative, and the whole device illusory, without even the slightest warning to the switchboard-attendant. For this reason it is advisable to arrange for a certain reserve and instal three-pole relays in both machine- and feeder-circuits. The extra cost and complication entailed is trifling compared with the great saving incurred on the outbreak of an accident. When the neutral point of the alternator is connected to earth, there is, of course, no alternative and relays must be placed in the three poles.

ARRANGEMENT OF COMPARTMENTS FOR HIGH-PRESSURE
APPARATUS.

Referring to the classification of the high-tension compartments on p. 4, it can now be understood that these heavy circuit-breakers require correspondingly spacious compartments. The high-tension gear must be placed in different galleries on account of the larger head-room necessary. A different method of disposing the compartments must also be adopted, because if they were placed in one row the total length of the masonry structure could not be kept within reasonable limits. To this end the compartments are placed alternately on either side of a central wall, so that those belonging to panels Nos. 1, 3, 5, etc., will be on one side of the wall, and those of panels Nos. 2, 4, 6, etc., on the other side. Distributing the high-tension compartments back to back in this manner has the further advantage of reducing the length of the bus-bars by one-half, and also the number of the supports, which are practically the only weak parts in a bus-bar system. There is, however, the inconvenience that the cables leading to or from the circuit-breakers pass between these and the central wall. This should be avoided if possible, as no cables whatever should be tolerated near the switches, with the exception of those necessary for connecting up. There are two ways of overcoming the difficulty. The first is to arrange for vertical trenches in the wall and to close them in front by cement or slate slabs: in the second, the cables are led up to the proper height on the other side of the wall in a separate compartment placed between two adjacent circuit-breaker cubicles. The latter method necessitates a longer masonry structure, but it has the advantage of leaving all cables free for inspection. The circuit-breakers shown in Figs. 15, Plate 2, lend themselves to an ideal cabling scheme, as the conductors enter and leave at the bottom of the switch and are taken in covered-in trenches to the neighbouring compartments, thereby leaving the operating mechanism completely free of all parts under tension.

In the St. Denis power-station¹ the circuit-breakers are disposed in two rows, but, instead of being placed back to back against a central wall, each row is mounted against a separate wall, leaving a passage between. Facing the engine-room in the first

¹ This power-station, of a total capacity of about 70,000 kilowatts, has been designed by the Société d'Électricité de Paris, and the switch-gear for the extensions is being executed by the Ateliers de Constructions Électriques de Charleroi.

row are the machine-, bus-junction, and feeder-group switches, whereas the second row contains only the feeder circuit-breakers. All cables leading to and from the switches are brought up on the back of the walls, and, after being connected to the instrument- and relay-transformers, pass through porcelain bushings to the switch-terminals.

With the back-to-back arrangement, when mechanically-operated circuit-breakers are employed the width of the operating-panels is preferably half that of the compartments. In this case a straight and direct drive between the operating-levers in front of the low-tension board and the circuit-breakers becomes possible, and as the panels and corresponding compartments face each other, the low-tension wiring may be arranged symmetrically.

EXAMPLES OF SWITCH-GEAR FOR STATIONS OF LARGE CAPACITY.

The switch-gears represented in Figs. 14, Plate 2, and Figs. 6, Plate 1, are typical examples for capacities of 10,000 kilowatts and 20,000 kilowatts respectively, the generating-units being for 1,500 kilowatts and 3,000 kilowatts, normal rating, at 6,500 volts.¹ Apart from certain minor differences, these two types are designed on the same lines. The high-tension gear is placed in three rooms; the transformer and discharger room, the circuit-breaker room, and the bus-bar room. In the first type the operating-board is placed in a separate chamber above the bus-bar room, which chamber is open on the machine-room side and provided with a gallery. The main circuit-breakers are all fitted with electro-magnetic control, because of the difficulty of disposing the driving-rods and levers for mechanical control. In the second type the panels are placed on a gallery, level with the floor of the circuit-breaker room, and the machine circuit-breakers are arranged for electrical control, whereas those for the feeders are controlled manually. The difference in the two examples is due mainly to the design of the buildings, but on the whole the second arrangement may prove more practical, as the important apparatus is within reach of the switchboard-attendant.

These two cases were designed with a view to underground feeders only, consequently the high-pressure bus-bars are situated in the uppermost part of the high-pressure galleries. It was only when

¹ The switch-gear for both of these power-stations was carried out by the Ateliers de Constructions Électriques de Charleroi, the second to the order of Messrs. Witting, Eborall and Company for the Port Dundas lighting-station in Glasgow.

the buildings were in an advanced state that overhead feeders were added in the first installation (Figs. 15), and cable connections had to be provided leading from the compartments in the basement to the lightning-arrester chamber, where the aerial lines start. For overhead feeders it is better to run the cables from the machines in a vertical line through the machine-apparatus and circuit-breakers to the bus-bars, and thence through the feeder-transformers and switches to the lightning-arresters; but on account of the line-protecting devices an extra gallery has to be added.

In dealing with these large capacities, it is imperative to adhere rigidly to the system of complete separation of the different poles. Each of the main compartments is therefore partitioned by strong vertical slabs of slate, soapstone, or ferro-concrete,¹ into three narrower cells. Wherever possible, the instrument-transformers ought to be further isolated from each other by horizontal barriers of similar material. The high-pressure bus-bars into which all the energy generated in the station flows, and from which it branches into the various distributing feeders, must be protected in the most careful manner. They are therefore mounted in long horizontal masonry conduits (Figs. 6, Plate 1, and Figs. 14, Plate 2), a separate structure being provided for each set of the duplicate or ring bars. This permits of cleaning or repairing one set without danger to the workman from the other set being alive. Unless placed in a special chamber by themselves, the bus-bars should be protected on all sides. They can be closed in on the front by armoured glass screens, fitted with handles, so that the screens may be easily removed; or, as is usual in American practice, they may be completely enclosed within the masonry structure, leaving doors for inspection opposite the supports only (Figs. 15, Plate 2).

As it is necessary, for cleaning or repairs, to isolate the compartments belonging to any one generator or feeder, section-switches are inserted between the oil circuit-breakers and the bus-bars. These section-switches are of the ordinary knife pattern, mounted on heavy, corrugated, porcelain insulators, and fixed to a slate or marble base as shown in Figs. 1, Plate 1. Unless very special precautions for insulation and earthing are taken, the contacts of section-switches should not be mounted on a common metal base-plate. The base-plate should be of some insulating material, to prevent the isolated apparatus from coming into contact with live parts, in case one of the porcelain insulators should break.

¹ Ferro-concrete has the advantage over the other materials of giving a maximum of strength for the same thicknesses. ' "

The section-switches are placed in separate compartments, either above the main circuit-breakers or behind the wall against which the bus-bars are fixed. In this latter case, the porcelain insulator supporting the bus-bar serves at the same time as a support for one contact of the section-switch. A copper stud passing through the insulator from the bus-bar supplies the necessary connection. Such an arrangement greatly simplifies the structure and reduces the cost of the apparatus and the cost of erection. The bus-bars are fixed by clamps, and as the drilling of holes is therefore unnecessary, any discrepancy in the distances between the supports need not be reckoned with.

ARRANGEMENT OF HIGH-PRESSURE CIRCUITS.

Simultaneously with the increase in capacity of the plant, greater elasticity of control becomes necessary, and the subdivision into sections is developed in such a manner that each of the powerful generating-units, with a certain number of feeders, constitutes a distinct group. These groups must, however, be capable of inter-connection to assure continuity of supply in the event of a breakdown.

The bus-bars are often arranged either in duplicate or on the ring-main system, and subdivided into independent sections. In the former case, all machines and feeders can be connected, by duplicate sets of section-switches, to both series of bars, so that no circuit need stand idle when a breakdown on one set of the bars occurs, or when cleaning or repairs are necessary. In a ring-main system where the various circuits are connected to one side only of the bars, and these are divided into several sections, any circuits connected to an isolated section must necessarily remain idle. The two systems may, however, be advantageously combined, especially when dealing with a large number of generators and feeders, as the total number of circuits can then be subdivided into independent groups. This provides additional security against a general shut-down of the station, consequent upon the failure of any one group. An example of such a combination of systems is shown in Figs. 6, Plate 1.

The same objection that holds against the obsolete ring-main system of steam-pipes for power-station work ought to be applied to the ring-main system of high-pressure bus-bars. In stations of small capacity it is from its comparative simplicity often desirable, especially as it has the additional advantage that the total outgoing energy can be easily measured; but it is not recommended for stations of large capacity. Further, this system requires the greatest length and weight of copper bars and the most masonry, and all

combinations have to be effected with the section-switches in the bus-bars, which operations are always attended by a certain amount of risk.

When the number of feeders becomes very considerable, as for instance in the cases of the Main Rapid Transit Generating-Station in New York, and the Lot's Road Generating-Station in Chelsea¹ (about seventy feeders in the latter case), it becomes imperative to dispose the feeders in groups, each with their own separate bars, these groups in their turn being branched off the main bus-bars. The two cases differ, however, with regard to the system of bars. In the first instance, which may possibly give a wider range of action but is slightly more complicated, duplicate bars are used (*Fig. 7*), whereas in the second case, only a single line of main bars is employed, but these are subdivided, each section being fed by two alternators (*Fig. 8* and *Fig. 15*, Plate 2). For paralleling and for facility of operation the main combinations are made by means of electrically-controlled non-automatic oil-break switches.²

The arrangement shown in *Fig. 8* represents perhaps the nearest approximation to finality in subdivision, namely, the "Complete Unit" system, as advocated by Messrs. Merz and McLellan in the Paper³ read by them before the Institution of Electrical Engineers in April, 1904. According to this system the entire power-house is sectioned into several absolutely self-contained units from boiler to feeder-cable, capable of interconnection only at the main steam-collector and at the main bus-bars. The arrangement of circuits in the St. Denis power-station is similar to that shown in *Fig. 8*, with the difference that there is only one machine per section and that tie-switches are provided between the feeder group bus-bars. This latter additional security was necessary in order to ensure continuity of service in case of one of the group-switches breaking down, more especially as many of the sub-stations are supplied by one feeder only.

To sum up, the system of bus-bars may differ greatly with the various conditions resulting from the character of the plant, the

¹ The switch-gear in the first case was carried out by the General Electric Company, of Schenectady. In the second case by the British Thomson-Houston Company.

² The question of the use of group-switches in large power-plants has been dealt with by Mr. L. B. Stillwell, in a Paper on "The Use of Group-Switches in large Power-Plants." Transactions of the American Institute of Electrical Engineers, vol. xxiii (1905), p. 199.

³ C. H. Merz and W. McLellan, "Power-Station Design." Journal of the Institution of Electrical Engineers, vol. 33, p. 696.

ARRANGEMENTS OF CIRCUITS WITH DUPLICATE MAIN BUS-BARS AND FEEDERS SUBDIVIDED INTO GROUPS. MAIN RAPID TRANSIT GENERATING-STATION, NEW YORK.

number and size of machines, and the nature of the feeder network.

As a general rule, however, too great a concentration of energy on any one part of the bars must be avoided, and provision must be

made to cut out any section easily and quickly without discontinuing supply.

To allow of the group- and bus-junction switches being isolated for inspection or repairs, they are connected by means of ordinary knife-switches to the bus-bars. When these isolating-switches are open, slate or marble plates, fitting into grooves cut in the barriers of the bus-bar conduits, can be inserted between the contacts. This permits of work being undertaken on the isolated section free of danger from contact with the bars under pressure.

With a view to avoid possible risk when working on the bus-bars, each section is provided with special earthing-switches, securely clamped to the bars in the most convenient position for making the connections to the earth-bar. Provision should be made, throughout the switch-gear, for earthing all ironwork, transformer- and instrument-casings, for the protection of the personnel from the danger of accidental contact between these parts and any high-tension conductors. With the same object, one pole of the secondary of all instrument-transformers should be earthed, so that protection is afforded in case of contact between the primary and secondary windings.

In order to lay out these earth-connections in all high-tension compartments and on the operating-panels in a neat and systematic manner, about eight or ten bars of hard-drawn copper are run the whole length of the gear, near such apparatus as is to be connected with them. These bars are interconnected at their ends and, if very long, at intermediate places. They are carried to carefully grounded earth-plates, of which there should be at least two. The introduction of these earth-bars greatly simplifies the low-pressure wiring scheme between the high-tension compartments and the operating-panels, as a common return can be used for all instrument-transformers.

AUXILIARY HIGH-PRESSURE APPARATUS.

All auxiliary apparatus, such as protective devices¹ against high-pressure discharges, cable-charging gear and ground-detectors, is

¹ These devices serve to guard against breakdown of insulation due to abnormal rises of pressure, caused either by electric oscillations when a change of circuit conditions takes place, or by atmospheric disturbances. The nature of the sudden pressure-rises in high-tension networks, as well as the character of suitable protective devices, has of late years formed the subject of both theoretical and practical investigation. Messrs. Steinmetz, Percy H. Thomas, Blondel and others, have contributed much to elucidate these phenomena, but as yet a really satisfactory solution of the problem of effective protection remains to be found.

disposed, with regard to its isolation from neighbouring parts, according to the rules which hold good for the main gear. The high-pressure limiting devices, which are connected with the feeder-circuits, and usually take the form of a number of spark-gaps in series with either carbon or liquid resistances, are generally placed in the same compartments as the instrument-transformers (Figs. 6, Plate 1), or in separate cubicles of their own (Figs. 15, Plate 2).

Lightning-arresters, with their non-inductive resistances and choking-coils,¹ such as are employed in the case of overhead feeders, are best disposed in the top gallery near to the outgoing lines. Great care should be taken to lead the conductors up to this apparatus in as straight and direct a line as possible, in order to avoid the efficiency of the arresters being partially destroyed by self-induction in the connecting wires.

In order that the dischargers may be easily inspected and cleaned, without shutting down the feeders, they are connected with the latter by isolating-switches. When a feeder-compartment has to be isolated, this must be done not only on the bus-bar side but also on the sub-station side. Hence section-switches are inserted between the apparatus and the cable junction-boxes, and all danger of contact with the live cable is averted. For further protection, special earthing-switches are provided, which have to be closed before starting on repair-work. The three sets of isolating-switches—for the dischargers, for the feeders, and for earthing—may be united, and mounted on the same base-plate, each pole being on a separate plate, thus forming a triple switch per pole.

Provision is usually made for bringing the outgoing feeder-cables² up to normal pressure before they are switched on to the main bus-bars. This may be effected by charging the cables either with one of the main machines or with an auxiliary motor-generator; by employing the Ferranti liquid resistance; or by the application of the Partridge transformer system. In all cases the arrangements required on the high-tension side of the board are the same.

¹ Recently it has become the practice to connect each phase of the high-pressure system (bus-bars) permanently to earth by means of "water-jet resistances." According to all accounts from installations where this apparatus has been adopted, the results seem to be very satisfactory. The permanent loss due to leakage to earth is trifling when compared with the gain in safety.

² With well-insulated cables and the employment of oil-break switches, the necessity of special devices for switching the cables in and out of circuit no longer exists in the same degree as formerly, when cable-insulation did not attain the perfection of the present day, and when air-break switches were in vogue.

The Ferranti resistance (*Figs. 9*) consists of two cast-iron vessels per phase, filled with acidulated water, and connected by two metal rods, the upper ends of which are connected together,

while the lower ends plunge into the vessels. The six rods are fixed to a common frame, which is raised or lowered by cords, operated by driving mechanism from the switchboard-platform. Each phase of the resistance should be placed in a separate masonry cubicle.

In the Partridge system (of which the connections are shown in *Fig. 10*), a transformer is used, large enough to furnish the charging-current for the longest feeder. One end of the primary of the transformer is connected, by means of two circuit-breakers, to either set of main bus-bars; the other end to an auxiliary set of bars,

which may be coupled to any of the feeders through a quick-break oil-switch. They, with the feeder in circuit, are then raised to the pressure of the main bus-bars, by decreasing the resistance in the secondary of the transformer, when the main circuit-breaker in the feeder-circuit is closed. In switching out,

the reverse process is adopted. The two circuit-breakers connecting the auxiliary with the main bars are provided with automatic overload release, and must be of the same size as the main feeder circuit-breakers on account of the power behind them. The auxiliary oil-switches may be of small capacity.

Of all devices for charging cables the Ferranti liquid resistance is certainly one of the simplest, and, on account of its mechanical design, the most reliable. It can be used for any kind or length of cable, without fear of resonance-effects such as may happen with the transformer system. Should the apparatus be kept in the circuit too long, the only result is that the water evaporates, whereas transformers may burn out and cause serious short-circuits.

An arrangement of cable-charging gear is shown in *Figs. 11*, where the auxiliary bus-bars, with the necessary non-automatic oil-switches, are disposed in a separate masonry structure.

In modern power-stations a permanent water-resistance is usually provided for loading up and testing the machines, and also for calibrating the instruments. The water-tank is built of concrete, lined with cement, and has the necessary pipe and valve-fittings for controlling the water-circulation. The electrodes, which are connected by flexible cables to fixed terminals, are suspended by cords from pulleys above the tank, and they can be lowered or raised by mechanical means according to the power to be absorbed. The size of such a tank for 2,000-kilowatt machines would be about 10 feet by 10 feet by 8 feet; and, as space is often an important factor, this capacity will be ample for far larger units, granted a sufficient water-supply for quick circulation. Control-panels with the necessary instruments are erected near these tanks to facilitate regulation of the energy absorbed.

Where cable-charging gear exists, the machines can be connected by means of the auxiliary bars to the testing-resistance (*Fig. 10*) instead of providing special cables for the purpose. To prevent interference with the charging of feeders the auxiliary bars must, of course, be suitably subdivided.

It is the usual practice to provide ground-detectors which indicate the insulation of the network, and thus permit of remedies being applied before complete failure of insulation has taken place. These detectors consist either of low-tension voltmeters and lamps connected through transformers to the high-tension bus-bars and to earth; or, of electrostatic voltmeters, branched directly off the high-pressure bars, or off condensers in circuit with them. A fourth voltmeter for measuring the pressure between the bars may be inserted between each leg of the system. The three or

ARRANGEMENT OF HIGH-PRESSURE SWITCH-GEAR SHOWING DISPOSAL OF CABLE-CHARGING APPARATUS.

four voltmeters, as the case may be, are joined up to the main high-tension bus-bars by means of oil-break switches which are interlocked with each other. All this apparatus is placed in a special masonry structure, separated from the rest of the high-tension apparatus, and within easy reach of the attendant (Figs. 6, Plate 1). In cases where feeder-charging gear is provided, the leakage-detectors may be arranged so that they can be connected to the feeder for testing purposes, while the feeder is being charged and before it is switched on to the main bus-bars, as shown for instance in *Fig. 10*.

The other device, which is often employed, consists of a three-phase star-wound transformer connected with the bus-bars through switch fuses, and with its neutral point earthed while the test is being made. The secondary of the transformer is wound in triangle, and a lamp, or voltmeter, is placed across each phase. Should one phase on the high-pressure system go to earth the lamp on that phase will be extinguished, thus indicating a fault.

LOW-PRESSURE CONTROL-GEAR.

In small plants all the low-tension instruments, meters, and apparatus may be placed on one board; but it is better in more important work to subdivide the low-tension gear. That portion of it necessary for the operation of the machines—starting up, paralleling, regulating, and shutting down—is placed either on a bench or on columns in front of the panels, and facing the engine-room (Figs. 15, Plate 2). The other portion, now consisting only of relays, the watt-hour meters, and the apparatus for the control of the exciter-circuits, is mounted on the low-tension or instrument board. When independent exciter-sets are used, a further subdivision may be made by placing the gear controlling these sets on a separate board, which could also contain the apparatus for the station-lighting and power-circuits. Further, by placing the synchronizing-instruments¹—the machine

¹ The adoption of electrically-operated circuit-breakers has made the use of automatic paralleling-devices possible, thus relieving the switchboard-attendant of a rather onerous duty. The condition of synchronism being equality of phase, periodicity, and pressure, successful paralleling depends on the moment for connecting the two circuits being properly timed. To render this manoeuvre automatic, suitable relays are provided, and when coincidence of the above-stated conditions is attained, these relays close the circuit of the driving-magnet, or motor, of the circuit-breaker, thus operating the latter. Several such synchronizing-devices have been brought out lately, and have been in successful operation in some of the large stations for the last 3 years.

and bus-bar voltmeters, the rotary synchronizer, and the synchronizing-lamps—together on a separate column, provided with a swivel headpiece, the instruments may at any time be turned to the most convenient angle at which they can be read from all parts of the operating-bench.

The separation described above greatly facilitates the duties of the engineer in charge of an important plant, as he is able to confine his attention while operating or, more especially, during breakdowns, to a fraction only of the whole switch-gear.

Separate columns (*Fig. 12* and *Figs. 14, Plate 2*) for each machine-unit are in many cases preferable to the bench-board, but where the latter is adopted its size should be restricted (by using edgewise instruments) and it should contain only the apparatus directly necessary for the control of the machines, the bus-junction switches, and the feeder group-switches. It would be mistaking the object of the whole design to do away with the instrument-board, and encumber the control-bench with such details as relays, energy-meters, power-factor indicators, and all the bars and connections appertaining to these. In the St. Denis power-station the low-pressure control-gear is divided into sections corresponding with the high-pressure units, and is mounted on a series of benches disposed directly above the high-pressure compartments, along the entire length of the switch-gear annex. Control from these benches would, however, be very difficult, owing to the great length they occupy, and therefore a "central control-board" is provided from which, under normal service conditions, operations are carried out. The "direct control-boards" merely form a reserve in case of accident. All machine circuit-breakers and bus-junction and group-switches, as well as the alternator field-regulators, are arranged for manual operation from the direct control panels and for electrical operation from the central board.¹

An important accessory to a modern switch-gear installation is the provision of signalling-apparatus, to enable orders given by the operator on the control-gallery to be transmitted to the man in charge of the machines. The simplest method would be to arrange a signal-bell and a few glow-lamps of different colours; for a power-station of some importance, however, a more elaborate system, similar to that used on ships, will be advisable.

When dealing with large generating-units, it has been found

¹ This combination of direct and central control with manual and electrical operation of the main high-pressure switches, is due to Dr. A. Della Riccia, Chief Engineer of the Société d'Electricité de Paris.

expedient to place near each machine an extra control-column, containing an ammeter, wattmeter, voltmeter, and the lever for the operation of an oil-break switch, so as to give the engineer attending

the machines complete control of the whole units—turbine or steam-engine, and generator. This arrangement is highly desirable for starting and testing, and in case of accidents. The current- and

potential-transformers for the instruments on the column, as well as the oil-break switch, are placed in masonry compartments in the basement. The switch, which is identical with the main circuit-breakers, minus the automatic devices, should in addition be provided with electrical release, so that it may be opened from the switchboard-platform. It would thus form a reserve, in case of emergency, to the main circuit-breaker. In fact, it may be advisable to cut the machines off the bus-bars first with these auxiliary switches, and only then open the circuit-breakers.

SWITCH-GEAR FOR AUXILIARY MACHINERY.

In the "Complete Unit" system all secondary machinery appertaining to one unit (such as the motors for ash-handling, air-pumps, circulating-pumps, economizers, fans, stokers, and exciters) is supplied from a transformer connected with the primary circuit of this unit. This system certainly has great merits for very high capacities, such as have been adopted during the last 3 or 4 years. The usual practice hitherto, however, has been to run this secondary machinery off auxiliary sets. Each motor should be joined to a different section of the main high-pressure bus-bars. The necessary switch-gear should be subdivided like the high-pressure gear, in order to avoid difficulties in case of a breakdown. It could at least be divided into two halves, with the machine-panels in the middle and the various feeder-panels arranged symmetrically on either side. Section-switches in the bus-bars would permit of either side of the board being used independently of the other. This entails practically no extra cost, and the gain is of great importance in case of repairs or extensions having to be carried out. Wherever possible, this sectioning should receive attention in designing alternating-current instrument-boards.¹

Various arrangements have been adopted for the auxiliary plant required for the excitation of the alternators. It is not unusual in stations of small output to provide an exciter for each alternator and to couple it either direct to the shaft of the main machine or drive it from the main machine by belting. In more important installations

¹ This symmetrical arrangement, as indicated for the auxiliary switch-gear in power-stations, might well be adopted in many cases for continuous-current traction and lighting-boards, instead of the system with the machines on one side and all the feeders on the other, with the impossibility of carrying out any work whatever on the board without either risk to the operator or shutting down completely.

the exciters are either direct-coupled or driven by independent engines. In many cases exciter-sets consisting of motor-generators are adopted in conjunction with a storage-battery. Other combinations, of course, are made to suit the special conditions of each individual plant.

Here again the switch-gear required must be designed with due regard to the condition that none of the main units ought ever to stand idle through a breakdown on any part of the excitation-machinery. A reserve supply of energy for excitation must be available, and the scheme of connections must be such that the field-windings of the alternators can, without loss of time, be switched off their normal supply-circuit on to the stand-by. In the case of direct-coupled exciters, these must be able to supply the excitation-energy required by the main units to which they are coupled, and to one or more of any other units whose exciters may have broken down. For this purpose a set of excitation bus-bars is provided, to which any exciter and any alternator field-circuit may be connected. When dealing with motor-generators in combination with a battery the latter usually serves as a stand-by, and arrangements should be made which will enable the excitation bus-bars to be switched on to the battery-bars.

The diagram of connections, Fig. 13, Plate 2, shows, for instance, a case where direct-coupled exciters are employed in conjunction with a battery. In the field-circuit of each alternator, a double-pole throw-over switch is inserted, permitting the machine to be coupled either with its own exciter or with the battery bus-bars.

Each field is of course provided with its own field-breaking switch and discharge resistance. The former is designed in such a manner that the field-windings are shunted by a non-inductive resistance before the field-circuit is opened. To enable the field-magnet windings to be completely isolated from the excitation bus-bars, for cleaning or for repairs, these switches should be of the two-pole type.

On account of the danger connected with the sudden opening of the highly inductive field-circuits, the field and throw-over switches are fitted with stops preventing manipulation until the catch is released. Safer than this device would be the interlocking of the field-switches with the regulators; no mistake in manipulating is then possible, as the field-switches can be opened and closed only when the regulators are in their zero position. They may also be fitted direct to the regulators, interlocked with these, and operated by their driving-mechanism. This would remove all heavy excitation-gear, such as bus-bars, throw-over switches, and connections

from the instrument-board, and would place them instead near the regulating- and starting-resistances, leaving free access to the many cables, terminals, instrument-resistances and shunts on the back of the board. Wherever possible the rheostats should be provided with mechanical in preference to electrical driving.

BUS-BARS AND CONNECTIONS.

Apart from the excitation bus-bars, which run the whole length of the alternator-panels, there are several other sets of low-pressure bars, mounted at the back of the operating-board. One of these sets is designed for synchronizing purposes, a second set serves for the operation of the circuit-breakers. When energy-meters and power-factor indicators are employed in the machine- and feeder-circuits, a number of current- and potential-transformers become necessary. Each set of instruments belonging to one circuit must, of course, possess its own series transformers; but a potential-transformer may be used in common for all the instruments (Fig. 13, Plate 2). To facilitate the connections between the potential-transformer and the instruments, a further set of low-pressure bars is mounted behind the instrument-board. Whenever two sets of main high-tension bus-bars are employed, one for lighting-circuits and the other for power-circuits, each series of main bars must be provided with its own pressure-transformers, and the low-tension bars must be duplicated. It may be noted that the potential-transformers employed for the instruments are also used for synchronizing.

The total number of high- and low-pressure and earthing bus-bars required for the switch-gear (Figs. 14, Plate 2) sums up as follows :—

(a) In the high-tension compartments :—

Two sets of main high-tension bus-bars, each set consisting of three bars.

One set of three auxiliary high-pressure bus-bars for the cable-charging gear.

Seven earthing-bars.

(b) Behind the low-tension instrument-panels :—

One set of two bars for the excitation of the alternators.

One set of two bars for the operating- and tripping-magnets (continuous-current) of the high-tension circuit-breakers

Two sets of two bars each for the instruments branched off the potential-transformers.

One set of bus-bars for lighting.

One earthing-bar.

All the low-tension bus-bars are of hard drawn copper of rectangular section and mounted on porcelain insulators. Only those for excitation carry heavy currents and are of comparatively large section ; but none of the low-tension bars should have a section smaller than 100 square millimetres, to ensure a thoroughly mechanical arrangement and allow the many small connections to be easily made.

The low-pressure connections between the various instruments should be laid out with great care, as a systematic wiring-scheme will render the arrangements more comprehensible, and will go far towards a good appearance of the back of the board. The small wires and cables are fixed, by means of insulating clamps, directly to the panels, thus leaving free access to the terminals of the instruments.

The back of the marble or slate panels should be painted with an insulating varnish before mounting the instruments or putting in the wiring, to prevent the otherwise inevitable stone-dust from soiling the various cables and apparatus.

The question whether all high- and low-pressure cabling belonging to the switch-gear should be insulated or not is one which has hardly yet received a definite answer. On the one hand, with non-insulated copper connections there is the danger to the personnel in case of accidental contact with live metal parts, and the danger of short-circuits. On the other hand, with insulated cable connections, especially when rubber is used, the risk of fire has to be taken into account. Insulating the connections, although more expensive, may, on the whole, be recommended. To obviate the risk of fire, all cables should be well separated from each other, and, whether for high or for low pressure, they should be protected with a double layer of asbestos braiding.¹ As the high-tension bus-bars are mounted in masonry compartments and can be isolated into sections for cleaning and repairs, no further protection is necessary. The low-tension bars, when they are of comparatively small section, should, however, be insulated with several layers of tape and then varnished. Bus-bars of large section, constituted usually of two, three, or more bars in parallel, should be left uninsulated on account of ventilation.

¹ A good method of procedure for the application of this fire-proof covering has been mentioned by Mr. H. W. Buck and adopted by the Niagara Falls Power Co. Asbestos tape is soaked in a solution of silicate of soda until thoroughly impregnated. It is then, while soft, wrapped spirally around the cable. This covering quickly hardens and forms a coating like stone over the braid of the cable. It is essential that the asbestos covering, to be thoroughly effective, be put on the cable after the latter has been put in place.

But in this case they must be mounted in such a position on the board that they will be safeguarded from accidental short-circuits. Throughout the whole gear the character of all cables, of whatever polarity or tension, should be easy of identification, preferably by colours.

A matter of great importance in the arrangement of the high-tension gear is that all cable-tunnels or trenches, and the spacing and size of the floor-girders, should be carefully considered when designing the buildings. In fact, it is advisable not to approve the plans for the buildings until the general arrangements for the switch-gear have been satisfactorily laid down.

With regard to the section and contact-surfaces of conductors, it is advisable not to determine these values altogether according to the usual rule of 500 amperes per square inch for sections and 100 amperes per square inch for contact-surfaces. It is essential that these current-carrying parts should be designed to ensure the necessary mechanical strength, and it will be found that the allowance to be made on this account will necessitate sections far larger than those required by what has been described above as the usual rule. Especially for high-pressure work, where the contact-pieces of the section-switches, circuit-breakers, etc., are fixed to large porcelain insulators and mounted on heavy base-plates, the proportions of the various parts must be in harmony with each other. It is inadmissible to design high-tension apparatus, relegated to masonry compartments, on the lines adopted for low-tension apparatus mounted on the operating-panels and unexposed to the comparatively rough treatment the high-tension gear has often to suffer. Not only here, but in all switch-gear design, the dimensions of the various parts should be apportioned in a liberal spirit. Neglect in this respect is frequently costly and always deplorable. To cite an example. The primary winding of the potential-transformers which feed the various instruments on the board is often a cause of trouble. The output of these transformers is very small, only about 50 to 250 watts, and their primaries are usually wound with a very fine wire of small mechanical strength, which after a certain period inevitably gives way; whereas a slight increase in the first cost would have ensured a more lasting apparatus.

Reliability in the smallest constructional details is of the greatest importance when dealing with such a multiplicity of apparatus as is required for the equipment of modern power-stations. This is partly obtained by devoting the most scrupulous attention to the mechanical design, and by not attempting to make economies at the cost of quality.

[THE INST. C.E. VOL. CLXVIII.]

D

The Author wishes in conclusion to thank the "Ateliers de Constructions Électriques de Charleroi" for their kind permission to publish details relating to work which he has designed for them. Thanks are also due to Mr. M. B. Field, Assoc. M. Inst. C.E., for the drawings relating to the Ferranti circuit-breakers and cable-charging gear, and to Mr. H. O. Levis, Managing Director of the British Thomson-Houston Co., and Mr. S. B. Fortenbaugh, Electrical Engineer of the Underground Electric Railways Co. of London, through whose kind offices it has been possible to embody in the Paper the drawings relating to the Chelsea generating-station.

The Paper is accompanied by tracings and sunprints, from some of which the Figures in the text and Plates 1 and 2 have been prepared.

H.W.E.I.E. FANTU.

ELECTRICALLY-OPERATED THREE-POLE OIL CIRCUIT-BREAKER. 3000-KILOWATTS NORMAL RATING, 10,000-VOLTS.

HIGH-TENSION SWITCH-GEAR.

Fig. 1 1 Inch = 6 Feet.
 Feet 5 4 3 2 1 0 5 10 Feet.
 Inches 12 6 0 3 2 Feet.
 Fig. 3 3/4 Inch = 1 Foot.
 Inches 12 6 0 3 2 Feet.
 Fig. 4 1 Inch = 2 Feet.
 Feet 10 5 0 10 20 30 Feet.
 Fig. 6 1 Inch = 16 Feet.

Alternating Current
Continuous Current
Earth Connections

Fig. 15 1 Inch = 12 Feet

HIGH - TENSION SWITCH - GEAR .

CROSS SECTION

LOTS ROAD GENERATING-STATION, CHELSEA.

FRONT ELEVATION