SYNCHRONISM.

BY PROF. EDWIN J. HOUSTON.

Among the many practical problems whose solution has long been sought for, but sought for in vain, until very recently, is the problem of obtaining approximately absolute synchronism.

A pendulum completes its to-and-fro motion, or oscillation, in a given time, that is independent of the distance through which it swings, or, in other words, independent of the amplitude of its oscillation. The time required to make one complete oscillation being exactly the same as that required to make any subsequent oscillation. This fact is expressed when we say, that the oscillations of a pendulum are isochronous.

When we include the idea of any one event happening in exactly the same time as that required for another event to happen, we express this fact correctly by saying that the movements of the two are synchronous. That is to say, the two not only start together, but complete all parts of their motions in the same time.

In order to render the preceding clearer, let us suppose that two tuning forks be started in vibration. Either fork will continue to make isochronous vibrations, if the time required by such fork to complete any single vibration is the same as that required to complete any subsequent vibration. While the vibrations of either fork may be isochronous, it does not follow that the vibrations of the two forks are synchronous.

Either of the two forks may be isochronous in its motions, although one of the forks may make 256 vibrations per second, while the other makes 512 vibrations per second. Either of the forks is isochronous, because it requires the same interval of time to complete any single to-and-fro motion; but the two forks are not synochronous, since one of them makes 256 vibrations per second, while the other makes 512 vibrations. In order that they may be synchronous they must each make the same number of vibrations in the same time.

The modern idea of synochronism includes the additional notion that the two bodies must not only move through the same distance in the same time, but that also their motions during the

entire time must be exactly similar, that is to say, that they must be synchronous at all points during their movements.

Let us suppose, for example, that two pendulums be started at exactly the same time and be permitted to swing for, say, one minute. It does not at all follow that because they make the same number of oscillations during that time that their oscillations have been necessarily synchronous throughout the entire time of their movements, that is throughout the entire minute; since, in accordance with the definition of synchronism we have above given, it is not only necessary that the two bodies shall have moved through an equal distance, or, in other words, shall have started and stopped at the same time, but that they shall have been synchronous in their movements throughout all parts of the entire number of vibrations made.

Many attempts have been made to attain synchronism, but up to within comparatively recent date, it would seem that these attempts have been unsuccessful in obtaining the synchronism to which reference have just been made; that is the synchronous movement, for an indefinite period of time, of free moving bodies mechanically independent. For example, a ratchet wheel and cog-wheel, controlled by pawls, star wheels, friction or other mechanical devices may be approximately synchronous in their movements, but with such movements I do not propose to treat, since they could not well be otherwise than approximately synchronous, and are not involved in a proper understanding of the term.

For example, the House Printing Telegraph, Hughes' Printing Telegraph, Calahan's Stock Printing Telegraph, Edison's Chemical Stock Printing Telegraph, Meyer's Multiplex Telegraph, Baudot's System of Telegraphy, Casselli's and Bonnelli's Autographic or Fac-Simile Telegraph, and Edison's Autographic Telegraph, are all operated by mechanically synchronized movements, which are brought into unison at given times by certain mechanical devices electrically controlled, which bring them to a full or partial stop by certain mechanical impediments, frictional or otherwise, to their free motion, and these corrections being in all cases pre-arranged, are made use of whether the movement of the machine requires them or not.

Such movements, however, are not comprised in the idea of synchronism as it has been above defined, nor are they worthy the designation of synchronous movements, since their move-

ments are never free or independent of mechanical appliances. They merely afford instances where different apparatus are maintained in a somewhat approximate synchronism for a very brief interval, when they are stopped, brought into unison, and again started.

A considerable stride in the direction of true synchronism was made by Prof. Paul Le Cour, of Copenhagen, whose genius has created the phonic wheel, a contrivance by means of which a rapidly interrupted circuit in an electro-magnet keeps in even rotation an armature wheel, the impulses of the magnet being made effective by increments so fine on the armature wheel that a uniform movement, hardly attainable by any other known device, is produced.

In strong contrast with the previously mentioned efforts towards synchronism, we have to-day the practically perfect synchronism of Mr. Delany, who, with marvellous ingenuity, has succeeded in obtaining and maintaining synchronism in the highest and best sense of the term.

I will be better understood when I call your attention to the fact that he has succeeded in keeping two bodies, separated by hundreds of miles, in synchronous rotation for periods of upwards of seventy hours, without variation during that time of the $\frac{1}{1000}$ part of a second. This is equivalent to two entirely independent bodies, separated from each other by hundreds of miles, starting together and passing through a distance of nearly one hundred miles without varying the $\frac{1}{100}$ part of an inch in that entire distance, or the $\frac{1}{1000}$ part of a second during that entire time.

The period of seventy hours I have mentioned, has no significance, so far as the limit of time is concerned, since these movements can be maintained for weeks, or months, or even for an indefinite period, with a like degree of accuracy; it being only necessary to keep the Voltaic batteries, used in this system, in working order.

Mr. Delany has chosen for his system the phonic wheel of Le Cour as affording the movement the best suited for regulation by his synchronizing device.

I will pass over the results he has already obtained in the shape of multiplex telegraphy, which, as you are probably aware, has been in successful practical operation under his system for some months past. In this system, circuits, ranging in number from six to seventy-two, according to their capacity, have been obtained over

a single wire, admitting of the transaction of from six to seventy-two separate messages, at practically the same time, either all in one direction, or any portion of the whole number in opposite directions. These circuits so obtained may be adapted to the Morse system or to the printing system, the Morse system being applicable up to twelve circuits at the ordinary rates of transmission; the speed of any number of circuits being dependent on the number of connections that any particular instrument gets with the line in a given time.

The operation of the Morse system by the Synchronous method involves a feature that has probably never been explained, and to it I will therefore call your particular attention. If we consider that for one complete rotation of the synchronized distributor, which constitutes one end of the line, the line passes over 72 contacts, which may be used for the transmission of messages, and, that under the sextuplex organization, each of the six operators' instruments would be connected to twelve of these contacts in the circle, and that the distributor rotates at the rate of $2\frac{5}{8}$ times per second, we will find that each of the six operators' instruments would be connected to the line 12 times for each complete rotation, or 34 times per second, and that all these operators have been put in connection with the line, and with their correspondents at the distant ends, through the synchronized distributor at that point, 34 times in a second. Now while one operator is making the shortest character or letter in the Morse alphabet, which is the letter *e*, consisting as it does of a single dot, let us see what takes place while this single dot is being transmitted. Let us imagine that when the first operator touches his key, and depresses it for the shortest interval of time that he is capable of holding it depressed, the distributor with its trailing finger, which is the end of the line, passes over one of the 12 segments connected to this operator's instrument, and transmits to the other end a portion of this single dot, but does not complete it until the other five operators have been placed in connection with the line, and the second, or third segment of the first operator's circuit has been touched by the trailing finger when the single dot representing the letter *e* is completed. Thus one dot is made up of two, three, or more shorter impulses, which manifest themselves on the polarized relay at the distant end, as one short signal, notwithstanding that portions of letters or characters have been transmitted by five other operators between the time of the beginning and the completion of this single

dot. This is an irrefutable evidence of a synchronism that has never before been more than contemplated as but a remote possibility.

The operation of the printing instrument by this system is another illustration of the degree of perfection of Mr. Delany's synchronism, that is hardly less striking than the foregoing; since if seventy-two printing instruments are used, each instrument must be dependent on a single segment for its message, and an instrument at each end of the line being connected to a single segment correspondingly located; the distributor must connect the line with those single segments at precisely the same instant, otherwise no impulse for the indication of a letter on the type wheel will be received. Theoretically it might be supposed that the transmission of a signal, say from Philadelphia to New York, by an instrument connected to a single segment, would not necessarily require that the trailing finger in the New York instrument should be on the corresponding single segment at the time that the signal was sent into the line at the Philadelphia end. Or, that the trailing finger on the New York instrument might be one segment behind the segment corresponding to the segment on which the signal was sent into the line at Philadelphia, and that still that the signal could be received on the corresponding segment in the New York instrument, since the time required for that signal to pass and manifest itself in New York would be sufficient to allow the New York instrument to reach the segment corresponding to the one from which the signal was sent into the line from Philadelphia. The fact that it takes time for the transmission of signals according to the distance and other conditions not necessary to discuss here, no one will dispute it, but, that this time admits of variation of movement or departure from synchronism in Mr. Delany's machine, is disproved by the machines themselves, for, if another instrument be connected to the next adjoining single segment in each machine, and a signal be sent from *New York to Philadelphia* immediately after, or within about the $\frac{1}{800}$ part of a second afterward, the signal from New York is received in Philadelphia as perfectly as that from Philadelphia was received in New York, thus, showing conclusively that the conditions of variation before referred to cannot have existed, since otherwise no signals could be received from New York or Philadelphia, over the second segment, as the Philadelphia

instruments would have left the segment before the signal could have been completed on the segment in the New York machine and transmitted to Philadelphia.

Probably the most extraordinary proof of practically absolute synchronism was demonstrated by the experiment recently made by Mr. Delany over the line between Boston and Providence, whereby a single dot was transmitted from Boston to Providence and automatically repeated back and forth over the same wire at practically the same instant of time, travelling over different circuits in rotation backward and forward for the duration of five minutes, during which time it traveled four hundred and fifty thousand miles, this time, of course, being almost wholly represented by the movement of the armatures of the instruments. When we consider, however, the conditions involved in the transmission of a single dot, as in the case of the letter *e*, already referred to, the extent of perfection of the synchronism obtained will be understood.

Before concluding, I desire to call your attention to some contemplated applications of the wonderfully complete synchronism of Mr. Delany which he has conveyed to me. Among some of these may be mentioned fac-simile transmissions of the reproduction of signs, characters, or hieroglyphics. For instance, a fac-simile copy of a dispatch, a drawing of a map, or a pen portrait of an individual may be transmitted to any distant point. The prime condition necessary being synchronism; so that the time is probably not far distant when the civil authorities can render the identification of criminals almost certain by having their portraits in the hands of an officer on the arrival of the train upon which the criminal has fled. Or, a newspaper in these days of enterprising journalism, many have transmitted for publication a sketch of a great public disaster or of any other event calling for illustration.

In conclusion, permit me to say that the invention by Mr. Delany of practically complete synchronism would appear to go no little ways towards the solution of a problem that stares practical men so squarely in the face. I allude to the problem as to what shall be done with the electric conductors that are strung over the houses and through the streets of our large cities. Whether these wires are to be placed underground or are to continue overhead, is a problem which in my opinion, is as yet far from being solved. The increased capacity which Mr. Delany

has obtained for every wire will, it is clear, greatly decrease the number of wires required for actual use and this makes the problem referred to somewhat easier of solution.

DISCUSSION.

Prof. HOUSTON :—I would say here, however, that Mr. Delany's system is not necessarily dependent upon the phonic wheel, as he has invented a magnetic motor which, when placed in connection with his automatic system of control, is capable of and containing exactly similar effects as are obtained with Lacour's phonic wheel.

Mr. Delany has very recently made an experiment on the telegraph line of the Pennsylvania Rail Road, and has sent messages from Philadelphia to New York and back again to Philadelphia. That was done last Sunday. I don't know how many relays were worked, but it worked successfully on the Pennsylvania lines.

In concluding this paper, I may mention, that I have had some conversation with Mr. Keith as to whether or not it would be advisable to go into a discussion of the means by which Mr. Delany has obtained his synchronism, and we came to the conclusion, that the time available to us is so short, that it would be worth while to go over the description of the means, which we can fairly suppose you are familiar with. Mr. Keith tells me, that when he publishes this paper, he will probably reprint some of the articles that I have written, which contain a full and exact description of the methods employed. Otherwise it would be difficult to compress any description of the system in the space of an hour. I see, very fortunately, that Mr. Delany is here himself, and if there is time, I would suggest, that he be called upon.

The CHAIRMAN (Mr. W. D. Sargent):—Mr. Houston has given us a very interesting paper. As I understand, Mr. Delany is here, and our time is limited—but we would be glad to hear from Mr. Delany.

Mr. DELANY :—I don't know as I have anything to say, unless some persons, not understanding the theory and principle of synchronism, would like to make inquiries, if so, I would be very glad to respond.

So far as an explanation of the system is concerned, I think it would be much more satisfactory, individually and collectively, if we would go to the exhibition and see the system in operation. There every facility is at hand to make a much clearer explanation

as to how it is done, and that certainly would be much more satisfactory than anything I would attempt to do here. However, if any of the gentlemen have anything to inquire about, I would be very glad to enlighten them as far as I can. I take pleasure in extending to the gentlemen of the conference here a cordial invitation to come out and see our system in operation in the exhibition building. We will be there during the week, and when they come, if they will make themselves known, I shall take particular pains to show it to them.

The CHAIRMAN:—Your apparatus in that building is simply working in the building?

Mr. DELANY:—We have no outside facilities at all. On Sunday we worked from Philadelphia to Jersey City and back over the Pennsylvania wires with a No. 9 and a No. 8 wire. One was an old wire, I don't know its electrical condition, it seemed to be in pretty good order.

Mr. MAILLOUX:—You are working through an artificial resistance, are you not?

Mr. DELANY:—Yes, our battery is very limited, consequently we are restricted to a lower resistance. On Sunday we had the Pennsylvania Railroad batteries, so we were able to work through to New York and return.

Mr. KINTNER:—What is the longest circuit you have worked?

Mr. DELANY:—We worked a year ago over the American Rapid Line from Boston to New York. We had then only progressed as far as the quadruplex.

Mr. KINTNER:—Do you find any static trouble over that distance?

Mr. DELANY:—There we had static trouble, but they were overcome.

Mr. KINTNER:—By ground contacts?

Mr. DELANY:—Ground contacts. This was entirely practical. The ground contacts afforded us a mechanical remedy for getting rid of the static troubles within our reach. For a longer distance, it would only be necessary to make the ground contacts a little larger.

Mr. KINTNER:—I was thinking of that.

Mr. DELANY:—Or larger than the contact connected with the operators' instruments. Of course such an enlargement would to a certain extent be at the expense of the operator's contact. If we have ground contact about the same size, so the line will have

the same duration with the ground that it had with the operator's instrument we can work very satisfactorily. The circuit referred to was 250 miles over a No. 8 galvanized iron wire. If it is necessary to work further over that kind of a wire we will probably have to put in repeaters or use a copper wire.

Mr. KINTNER:—Have you ever tried the condenser?

Mr. DELANY:—We could not use that very well, we could not apply the condenser, because our currents are constantly being reversed. We use polarized relays. So while it would assist in one instance, it would create a difficulty in the other.

Mr. KINTNER:—I had forgotten about the polarization.

Mr. DELANY:—We have worked successfully through three repeaters, and have worked through five; it was simply only necessary that the sounder of one circuit should become the transmitter in another circuit.

The CHAIRMAN:—To what extent is your system dependent upon the electrical condition of the conductor between the two ends?

Mr. DELANY:—We have but very little difficulty from that cause. Synchronism is maintained, if we get sufficient current over the line to actuate the armature of the correcting relay adjusted in the most sensitive way, the armature of the electromagnet is adjusted by a delicate spring, so as to keep the armature against the back stop. If we get a sufficient current over the line to move the armature from the back stop, we can synchronize. In fact we can synchronize further than we can telegraph. Any ordinary change in the condition of the line does not affect us at all, because frequently we have put three or four thousand ohms of resistance into the line, and taken it out suddenly without affecting our synchronizing apparatus. With polarized relays and reversed current a fluctuating condition of the line does not affect us as it would an ordinary relay. It is simply a question whether you get sufficient current over the line to actuate the most sensitively adjusted relay. As long as we can do that we can work.

Mr. MAYNARD:—Is it possible for these machines to get out of synchronism?

Mr. DELANY:—Oh, yes.

Mr. MAYNARD:—What do you do then?

Mr. DELANY:—They come in of themselves, if you let them alone within themselves two minutes. The correcting impulses sent over the line will correct a discrepancy in vibration of the

forks of about five vibrations per second. If you should open a wire between the two stations, the instrument would then have to run independently, they would get out of synchronism within a minute or two. The instrument may be locked up and not be accessible to anybody. If they should be thrown out of synchronism they would come to that point again of themselves.

Mr. MAILLOUX:—Do you maintain the line of circuit so they can keep themselves in a synchronal condition.

Mr. DELANEY:—Oh, yes; the line of circuit is always closed, subject to interruptions, of course, of the commutator from the circuit table.

Mr. MAILLOUX:—I mean when the operator wishes to send a message in the ordinary way, he does not have to wait until the line is synchronized.

Mr. DELANEY:—He has to wait until the line is synchronized to send the message; if he did not, the message would not reach the operators in connection with that circuit at the distant end.

Mr. MAILLOUX.—When the machine is in use on the line, I wish to inquire whether the machine is maintained in a synchronized condition?

Mr. DELANEY:—It is always maintained in a synchronized condition. Each operator's instrument is always to the ground, so that if the operator at the other end of the line closes his key, it is manifested directly to the corresponding operator at the distant end.

Mr. MAILLOUX:—It is your purpose, is it not, to maintain that local circuit in action all the time, so that the phonic wheel is moving all the time at either end?

Mr. DELANEY:—Always; at night we shut them down if there is no longer necessity for running them.

Mr. MAILLOUX:—You open in the morning and synchronize?

Mr. DELANEY:—After we start them in the morning they run all day.

Mr. MAILLOUX:—With the ordinary Morse system how many transmissions can be made practically and profitably over one wire.

Mr. DELANEY:—We make six transmissions by the Morse at the highest rate of the ability of the operator. That is, you can send forty words per minute—we have transmitted from Providence to Boston, and Boston to Providence and back to Boston by a line, which I suppose is a circuit of about 100 miles,

very close to 1000 words on the sixth of a wire, *i. e.*, when the wire was distributed sextuplex at the rate of from 43 to 44 words per minute. I received myself over a twelfth of a wire on eleven hundred words at an average of twenty words and a fraction. It is equal to 18 or 20 words beyond a doubt. Now as to the commercial advantages of either the six or twelve divisions of the segments that is a question. For the commercial telegraphy I suppose that between two offices doing an ordinary telegraph business, the six circuits could be worked to the best advantage, because it requires the less number of operators to the circuit, and each circuit is equal to the best ability of the most expert operator. But for renting purposes, you may rent twelve circuits to a greater advantage than the six; beyond the twelve we have to abandon the Morse system and use Printers.

FIGURE 1.