DISCUSSION.

THE PRESIDENT:—This paper is now open for discussion.

MR. CHARLES S. BRADLEY:—Mr. President, this paper is a little in advance of my mathematics. I do not mean to cast any reflection upon Mr. Kennelly at all. It is often said that the papers are too mathematical. I do not think that is true in this case; I did not mean to insinuate that it was. It is made as plain, I think, as any such matter can be made, and I think great credit is due to you both for bringing out such a paper as this; for most people want to conceal and keep back for their own use all of these very valuable considerations. This is going to prove of great value to the alternating current work, I have no doubt; I am very certain of it. Although I cannot fully follow it, I can follow a portion of it, and I must say it is very instructive. The wave is a very striking thing, indeed, and I can say nothing except to praise the paper. I am unable to criticise it.

DR. M. I. PUPIN:—I venture to offer one or two remarks only on the paper. I think that it is a very useful thing to have certain mathematical functions, with which we are not very well acquainted, worked out numerically, and, if possible, reduced to graphical representation. This is especially true of the so-called hyperbolic sine and the cosine. These are the functions which puzzle us considerably in the problem of transmission of current along a line possessing appreciable distributed capacity, self-induction and resistance. The problem is an old problem, and used to engage the attention of some of the ablest physicists. As far as I know, the earliest authority on this problem is Prof. Kirchhoff, the same man who discovered spectrum analysis. He attacked the problem in 1857, and gave us what may be considered a complete solution of it. This paper of Prof. Kirchhoff is memorable for several reasons, and especially because in this paper it was stated for the first time in the history of electricity, so far as I know, that under certain conditions the velocity of propagation of an electric wave along a conducting wire is equal to the velocity of light. The result was predicted on the basis of the old theory.

The other reason why this paper is especially memorable is this: Prof. Kirchhoff attacked the problem as a physicist would do; namely, he considered in the first place a system in which there are a certain number of forces acting. Then he considered the physical constants of the system, and looked then for the fundamental relation between these forces and these constants. This is, in fact, the method which is general to all the physical problems, whether electrical, mechanical or any other kind. The fundamental relation which he obtained between the impressed electromotive forces and the physical constants of the line, that is self-induction, capacity and the resistance per unit length, is strikingly the same as the funda-

mental relations which exist between the impressed forces on a flexible, suspended string and the physical constants of that string—namely, the weight per unit length, the tension, internal resistance, air resistance, etc. If the fundamental relation is the same in the two cases, it follows that the vibration of the string will follow exactly the same law as the transmission of an electric wave along the conductor, exactly the same; knowing one, we know the other. That is what I should call reasoning by analogy. It is not an analogy suggested by superficial observation, but it is an exact analogy. The employment of such analogies in our reasoning has been criticised lately on several occasions by people who ought to know better. Now, if we consider the motion of a string, we will get most of the results which the President and Mr. Kennelly have indicated in their very carefully worked out paper. We shall have what they choose to call resonance, when the energy which is communicated to the line reaches the end which is insulated, and is reflected, and the reflected wave and the incoming wave interfere and form stationary waves; and in a particular case, that is a case where we have no damping, of course, the returning wave would be almost as strong as the incoming wave, and we would have maxima and minima. The minima would be almost equal to zero. In this case they are not, because there is damping. Of course, it makes a difference whether the line is perfectly insulated or not. The damping factor, is the factor which consumes the energy of the wave. It is especially the ohmic resistance. The velocity of the wave, of course, as we all know, depends on the period of the wave. It is not the same for all periods. The wave is faster, the shorter its time of vibration; and the longer the time of vibration, the slower and the longer it is, and so on.

Now, Prof. Houston and Prof. Kennelly seem to be alarmed by the fact that certain people have made the very unscientific remark that transmission of energy can be effected more economically and better by a resonant line than by a line which is not resonant. That sounds to me like wanting to eat a cake and have it. The very fact that you have resonance means that you are accumulating something, that you are putting power upon a line without utilizing it. If you utilize it, of course then there is no cumulative effect, and there is no resonance. Mr. Kennelly has expressed that very well by saying that the resonance effects depend very much on the elastic reflection of the terminus of the line. Now in a great many cases we really do not care to transmit power in the ordinary sense of the word—that is, a large amount of power, over a long line. In these cases resonance, whether in this shape or in any other shape, offers considerable prospects. For instance, if we wish to transmit power to a certain point—a small amount of power—and we do not care what the efficiency of the transmission is, for in-

stance, in telegraphy or telephony, we really do not care how much we put in—within certain limits, of course—provided we can get enough at the receiving end. This is a point worthy of our consideration, and I was rather disappointed when I saw that Professors Houston and Kennelly did not discuss this problem more fully than they did. But still, along the lines indicated by them, I think the subject could be very easily continued.

I think Professors Houston and Kennelly deserve great credit for the extremely careful way in which they have worked out the figure of Plate I, and I am glad to hear that anyone who wishes to have this plate can have it in enlarged form, because it really simplifies numerical calculations very much.

Mr. President, I take the pleasure of introducing to the INSTITUTE one of our fellow members, Dr. Webster of Clark University, who takes great interest in the INSTITUTE. I have no doubt that the members of the INSTITUTE would be pleased to hear what Dr. Webster has to say on the subject of this evening; especially since he is interested in a line of work which is within the region of our present discussion.

THE PRESIDENT:—I am sure we should all be pleased to hear from Dr. Webster.

DR. ARTHUR G. WEBSTER:—Mr. President and gentlemen of the INSTITUTE, I hardly expected to be called upon to address you on this my first appearance in this honorable body, in which, as my friend Dr. Pupin says, I take great interest, although I live somewhat out of the radius of New York.

I am extremely interested in this subject. I have thought about it for a good many years, and I have listened with great admiration to the reading of the paper, which I was fortunate enough to be able to look over before coming here. Some of my preconceived ideas have received a considerable shock in the course of that reading. Not being an engineer myself, and not knowing engineers as well as I wish I did, I had supposed that an engineer was an extremely busy man and that he was mostly occupied in doing practical things which brought him in a certain amount of very pleasant returns which are not open to people in my own position. But I came to the conclusion that there are engineers who delight in doing other things, who are willing to do work in arithmetic, which I may say for myself I find a terrible grind. If I have been fortunate enough to get certain experimental results and put them down in my notebook, when it comes to working the calculations over, I should prefer to send them several hundred miles rather than do it myself. But I have come to the conclusion that business is probably a little slack in Philadelphia. I have always had the impression that there were more hours in the day in Philadelphia than in New York. But I see that there must be a good many more hours in the day, and a good many more days in the week, and if I might take the liberty I should be glad to ask Mr. Ken-

nelly privately how long it took him to draw that diagram. I was extremely interested in that part. I may say, in the first place that not having brought a dictionary with me I was a little at a loss for some of these terms ending in "ance," and if Mr. Kennelly's forbearance is as great as his admittance I will proceed to make a few remarks which I hope may be pertinent to the question. As I have said, it is extremely pleasant to find somebody who is willing to work out results which we may have had in formulas and to give us arithmetical results, with curves and pictures which it is pleasant to see and also to own. I am going to make a suggestion to Mr. Kennelly, which will entirely change the appearance of that plate, if he adopts it, although I do not expect he will, as the plate is engraved. As Dr. Pupin has said, this question is one of the most interesting in this department of mathematical physics, and has been so ever since it was taken up so long ago by Kirchhoff. All the results arrived at here to-night are probably in that paper. But it is very pleasant to think that when some eight or nine years ago I began reading the works of Mr. Oliver Heaviside, published in the London *Electrician*, before the advent of the omniscience which now rules in that quarter, I found that Mr. Heaviside had taken up the same problem and had come to the same results all by himself, and when he got all through he found that Prof. Kirchhoff had done the same thing twenty years before. That illustrates a disease peculiar to Englishmen, and others, of not reading other languages than their own, or perhaps not knowing that there are other languages than their own. I may say that whenever I want to know anything about alternating currents, before I understand it, I am obliged to sit down with my pen and go over the whole thing, as I did this afternoon—not understanding the terminology, I worked the thing out myself and presently I saw what was meant by all the terms. But I seldom spend very many weeks on a problem until I have looked over Mr. Oliver Heaviside's papers. Generally the solution is there. It is so in this case. It shows the advantage of being forewarned. Mr. Oliver Heaviside, of course, claimed some time ago from purely theoretical grounds when nobody was looking at him except Sir William Thomson, (I was looking at him too, but I will not name myself in this connection—I was one of the forty-nine who sent for a copy of his papers and got one), that the self-induction of wires was a very important factor in alternating current work.

I will now leave this and say that I enjoyed this part, and am glad that it has been done. It must have required an enormous amount of labor, and, after all, the conclusion seems to be that it *practically* does not amount to much. It has been a good exercise for Mr. Kennelly, different from what falls to the lot of engineers in general. As I say, Mr. Heaviside was one of the first to maintain from purely theoretical grounds that the induc-

tance of wires was very important for telephony and other things. It had been claimed by the dominant school, the government school, in England, that self-inductance was hurtful and could not do any good. Mr. Heaviside said otherwise. If Mr. Heaviside's controverters had had their way, probably there never would have been any long-distance telephone lines in the world.

Another thing that struck me in this paper was the power of abbreviation. As I say, I am not used to those terms. Some of them I have used a good deal, but these words in "ance," and these vectorial methods struck me a little strangely. But I soon saw what they meant. However, the problem, as Dr. Pupin has said, is simply the problem of an elastic string moving in a viscous medium. If it is stretched the required amount and fastened at the end, it vibrates in nodes and loops; but if there is a viscous medium, there is a damping, and what occurs here in the wire and in a string moving in a viscous liquid is that the velocity of propagation is not the same as it would be without viscosity. Instead of having perfect interference and getting perfect nodes, which do not appear in the figure, the waves going and returning being damped, do not completely neutralize each other, and the result is that there is never any reduction to zero.

Now to come to my criticism. I think Mr. Kennelly has overlooked one point. It occurs very frequently in mathematical physics that the differential equations involved are very simply solved—as in the case here, an exponential or trigonometric function will solve the differential equation. But the difficulty occurs, that in every problem, besides having a function to satisfy the differential equations everywhere, it must satisfy certain boundary or terminal conditions. Mr. Kennelly has considered the case of insulation at one end or connection with the ground. Those are very simple. What you want to know, I suppose, about a line carrying an alternating current is what will happen when there is a motor at the farther end. He has spoken of some lamps, but that he has not treated separately. Now, if you put a motor on there which holds back, there is certainly a difference. Imagine the case of the string. It is obviously a very different matter about pitch, wave-length and all that, whether you have the string fastened rigidly to two pegs at the ends, or whether you have it fastened to a weak spring representing capacity. If it is fastened to a weak spring, and you shake it at the other end, you do not have sharp reflections. On the other hand, if you have it connected to a weight which has inertia, there is another change in the motion—the reflection is different still. In the case of an alternating current motor, there is certainly self-induction. Now these things must produce a reaction there on the line, and cause a change of phase and giving out of power and all that. It seems to me, that it must be treated quite by itself.

Finally I am always delighted when I see a subject of pure mathematics brought into the field of applied physics, and especially by an engineer. The most brilliant case I recall of that kind was in the case of the French engineer Saint Venant, who solved most beautiful problems in elasticity and got formulæ which are now used by every engineer, I suppose. All engineers before had used an empirical method. The method that I speak of is the same there as here—the method of the application of the principle of the conformal development of one plane upon another. Perhaps some of you wonder how Mr. Kennelly got this Plate I. I did too, but I can guess. In Maxwell there is a chapter on the theory of conjugate functions. The point is to find in two planes points corresponding to each other, so that every line in one will correspond with a line of the other, and

FIG. 12.

$$\begin{aligned} x'' + i y'' &= \log (x' + i y'). \\ x' + i y' &= \cosh (x + i y). \end{aligned}$$

$\left\{ \begin{array}{l} x'', y'' \text{ are rectangular co-ordinates in this diagram.} \\ x', y' \text{ " " " " Kennelly's diagram.} \end{array} \right\}$

the property is that all angles made by corresponding lines are preserved in the two planes. Here we have the case of the x and y lines in one plane corresponding to the ellipses and hyperbolas in the other plane. This is done by the use of the analytic function, $\cosh (x + i y)$ which gives this development. Mr. Kennelly's result has been that you have to measure—having one curve $x = .2$, and the other, $y = .7$ corresponding on this diagram to the ellipse $x = .2$ and the hyperbola, $y = .7$; their point of intersection corresponds to the point of intersection of the straight lines, $x' = .2$ $y' = .7$. If we go one step farther and transform this plane again so that the circles in this plane go into straight

lines in a third plane, and the radii which cut these circles at right angles go into straight lines cutting the straight lines just mentioned in the third figure at right angles, we shall have to see what these ellipses and curves transform into. Mr. Kennelly will find the picture in Maxwell, and instead of having to draw an infinite plane he will have to draw only a strip of a finite width, 2π , which will represent the whole thing. See Fig. 12.

The axis of abscissæ here comes into a line in the middle of the figure and goes off to infinity; the middle of the figures go off into infinity and the ellipses go into curves like this, which come around that line. These ellipses pull out here more at the left, and these hyperbolas, which cut these ellipses at right angles, go into lines which cut these lines at right angles. Now you will not have to draw these extra sets of radii and circles which complicate the figure and cover it up with four sets of curves instead of two. All you have to do is to put this figure on coordinate paper, and then when you have measured off, instead of the straight line or ellipse marked $x = .2$, you will have the particular one of these curves marked with that value, and instead of taking a hyperbola you will take this other curve, and the point in question will be the intersection of the two. Instead of measuring this distance from any particular point and measuring an angle you simply measure these two rectangular coordinates. Mr. Kennelly has got the work all done in making this figure, and he has simply to transform this figure into that by taking points which lie on a circle here and marking them off. That will make it easier for the members of the INSTITUTE who are going to use this work of Mr. Kennelly's in their practical engineering to get the results, and they will not have so many lines on the figure. There will be nothing for them to do, and it will be a little further application of the same mathematical principle that he has already applied and might apply here.

MR. CHARLES CUTTRISS:—While I am not going into the mathematical discussion of this question, I would like to say that if I understand the remark of the last speaker correctly, he said that the curves described by the waves travelling through a cable, keep up a uniform period but merely flatten out in a perfectly uniform manner as they travel through the cable.

I would say that I have proved by experiments that this is not so. The cable experimented upon was over 840 knots in length, and the experiments were made for reasons that were very remote from the purpose of this paper.

You will hardly call the period or rate at which I transmitted the current, alternating current; it was about 80 per minute.

The potential began from zero, went up to 40 volts and came down absolutely in the same manner by the same gradation and time in which they went up, and a record was taken at the distant end of the cable on a siphon recorder. The wave, instead of going up in a perfect curve, such as you would imagine

and coming down on the opposite crest in the same curve, went up in an approximately perfect curve to the apex which was prolonged. The curve then dropped more suddenly to its zero, and in so doing, described almost a concave. This same formation is maintained in larger or smaller curves whether the speed be about 80 periods per minute or 360, the latter speed being the maximum at which I could transmit.

I do not know whether I have described the shape of the curve clearly, so I will try and put it upon the blackboard.

The curve, as you might imagine, rising from zero to 40 volts would be a perfect curve like this — instead of which its shape is more like that.

FIG. 13.

Now, that will prove that it is not the same as the pulling of a string and getting the same movement, only growing flatter and flatter as it travels along.

I have tried for a long time, for purposes which I cannot mention, to obtain this perfect curve, but hitherto have not been successful.

DR. WEBSTER:—If I may be pardoned for replying to the objection of Mr. Cuttriss, he has quite misunderstood what I said. I by no means stated that the thing would be the same all along the curve. The curve that he has given there is exactly what might be expected. The differential equations are the same as for a wave of water. You have seen the waves running along at sea. They look very much like the sinusoidal wave that we have so much in physics. But when they come in shore on the beach they curl over just like Mr. Cuttriss' picture. There is a figure like that. I cannot say exactly where it is, but I would be willing to wager that there is something on that in Mr. Heaviside's paper. But I am extremely glad he has experimented on it. I have often thought that if I had only some pull on a cable or cable official to make a few experiments I should be only too delighted. I want to ask Mr. Cuttriss a question I never have been able to ask anybody, because I never knew anybody who was in a position to answer it, that is, what is the self-induction of a real submarine cable per mile? If he will tell me that, I shall go home pleased.

MR. CUTTRISS:—That is something that has never been worked out.

DR. WEBSTER:—I have been engaged in experiments for quite a while on electric waves and such things, and I have got the apparatus for determining exactly that thing, if I only had the cable. I never expect to have the opportunity of doing it.

If it could be done, and if there was such a thing as a cable which was out of business for a few hours or a few days, we could learn a lot, and I am sure it would be extremely worth while. If there is anybody here that wishes to present a few million dollars or a cable to Clark University or any other, I should be very glad to lend my apparatus to have this done, and I am sure it would be worth while.

MR. CUTTRISS:—I beg to say that the great trouble is that you cannot be at both ends of the cable at the same time.

DR. WEBSTER:—I do not want to be. I have been planning a long time, in fact at the Congress in Chicago, two years ago, I announced my paper. I had done enough preliminary experimenting to think I had got the facts I wanted. I had the wires that came to the same thing as a cable, and I thought I had the results about these waves, but they were so extremely short, something like two or three millionths of a second, that I afterwards called myself down and withdrew the paper. I have not yet been able to get the wires up, and as Mr. Cuttriss said, get at both ends at the same time. But I can assure him it is not necessary to do that, and I think we can arrange the experiment at one end so that we can get all that we want to know.

DR. PUPIN:—Mr. Cuttriss remarked that in this case we have no resemblance between the pulling of the string and the actual propagation of the wave. Neither should we have, because in the case of a submarine cable, the self-induction is very small, and it is just like jerking at a string whose weight is small in comparison to the viscosity of the medium in which it is moving. Therefore in this case again, the fundamental equation reduces itself to the same kind which describe the conduction of heat. The analogy of the vibrating string ceases, passing into the analogy of conduction of heat. We pass from one physical phenomenon to another, from the vibration of the string to the conduction of heat. So far as the experimental work is concerned, Foucault and some French engineers have experimented on the transmission of signals through air lines, and they found the same difficulty that Mr. Cuttriss found in Atlantic cables, namely that the shape of the wave as it is put into the line at the sending end does not resemble very much the shape of the wave which appears at the receiving end. They found, unfortunately, that although they put in at the sending end a very sharp signal, at the receiving end that signal was not sharp, but it came just like a steep wave front, and then it dragged out into a more or less elongated tail; so that they really could not thereby determine the exact time at which the wave had arrived at the end of the line. But no experimental work has ever been done on these matters in the laboratory. Telegraph lines are always busy, and it is very difficult to perform experiments and be at both ends of the line. But experiments of that kind can be performed. We can make, without very much trouble, artificial

cables representing long air lines in all the particulars; that is having so and so much resistance per mile, self-induction per mile and capacity per mile, if we simply take the trouble; and I think it would be quite worth while to make some experiments in that direction, especially since the problem is very important and no experiments have ever been made in that line of work.

THE PRESIDENT:—If there is no other discussion, as the hour is late and there is another paper, I will call on Mr. Kennelly to close the discussion.

MR. KENNELLY:—The criticisms which have been raised are speedily dealt with in this case. First of all, in regard to terminal conditions, the head and front of the offending in our paper is alleged to be that, while we deal with an insulated line, and have also dealt with a grounded line, we have not considered the countless conditions that may practically arise where a line is neither insulated nor grounded, but is in some intermediate condition. If, however, you will examine formulas 3 and 4, you will see that they take into account every possible condition, providing of course, that the currents and electromotive forces are sinusoidal. We have, unfortunately, to make that assumption, which is not justified in every practical case, as we know. Look at equation 3, for example; the electromotive force is composed of two terms, the first of which depends on the terminal electromotive force, and the second on the terminal current. If the terminal conditions require that the lag in phase of the received current is a given number of degrees, insert that number of degrees in the current and the results obtained will be applicable to all points on the line. No lag was assumed for the current in Plate III, because there was no object to be gained by the selection of any particular phase difference between the received pressure and current. But of course, it is evident that any apparatus, as for example a transformer or a motor, when supplied with, say a thousand volts at the receiving end of the line, will take a certain number of amperes at a definite lag for any given load, and one is supposed to know experimentally what the lag at any given load will be. If we know this relation for all conditions of load, we simply have to interpolate in equations 3 and 4, in order to determine the pressure and current at any point on the line, provided it can be safely assumed that the current is sinusoidal. Of course, in a transformer or motor, the current is not usually sinusoidal, and of course, our formulas fail just to that degree. But we know also that we can make certain assumptions in regard to the deviation from the sinusoidal condition of even waves of current that have been distorted by hysteresis. We know that when a current is distorted by hysteresis in a transformer, we can separate the complex wave into two waves, each nearly sinusoidal, and this analysis will very closely represent the actual condition of affairs. I need only refer to Mr. Steinmetz' work

in this direction, as presented at the Philadelphia meeting last year, to show that that is the case, and therefore we claim that our formulas deal with every possible terminal condition. In the paper we have only illustrated a few terminal conditions, for the sake of simplicity.

We do not claim that we have deduced any absolutely new principles. We know that the fundamental principles dealt with in our paper have been developed long ago; but what we do claim is that we have presented them here for the first time in a simple and practical engineering form.

Now in regard to Plate I, and the question of the way in which it should be most conveniently drawn, we cannot agree with the suggestion of Dr. Webster, for the reason that what we seek is not the rectangular coordinates of a hyperbolic sine or co-sine, but its polar coordinates. In order to draw that diagram, we had to send to Europe for a machine. We could not find anywhere in this country a machine which would draw the lines accurately enough.

In regard to the question that Mr. Cuttriss has mentioned, of course his problem is entirely different from that which we here consider. He is dealing with signals representing the trace of current as they proceed over a long cable. We deal with the effective electromotive force and current, and not with the trace of any single wave. Those waves we show are simply photographs, so to speak, at any moment, of the effective alternating current pressure and current strength at all points along the line, and at all moments that condition will be maintained, although everywhere the current is alternately reversing in direction. We do not of course show what the trace would be of alternating current waves, as recorded for example by the siphon recorder.

WM. MAVER, JR.:—(*Communicated after Adjournment.*) I desire to express my appreciation of the valuable paper which Messrs. Houston and Kennelly have brought before us. It is doubtless true, as several of the participants in the discussion on the paper stated, that to many it will require considerable study before it is thoroughly digested and assimilated in its entirety, but fortunately the paper is on record and, therefore, accessible for study. Furthermore, there are numerous points brought out in plain language and others illustrated by numerical examples, which require only an ordinary understanding to grasp them.

Furthermore in my opinion, the paper is not only valuable but it is also timely, for so much has been said or intimated concerning the direful possibilities of the effects of resonance that some of us had almost began to think, despite years of practical experience with alternating current circuits, having considerable capacity and inductance, that some fine day resonance would astonish and confound us by upsetting things generally. For example, it was only recently that I was informed that resonance

had been held responsible for the failure of the insulation of an underground alternating current circuit in a neighboring city, which was proven by the fact that, upon changing the route of the circuit, the cable in question no longer broke down.

As my experience of over six years with more than fifty such alternating circuits, representing a total length of about 300 miles of underground cable, had not disclosed any similar case, I was considerably nonplussed. It is therefore reassuring to learn from Messrs. Houston and Kennelly's calculations, that the maximum increase of voltage due to resonance on a circuit such as the one I refer to would be, under the most favorable conditions, about one volt.

¶¶The paper further shows that even on the very longest aerial circuits the devices which may be provided to protect the insulation from the effects of lightning discharges may safely be left to deal with the increased voltage due to resonance.

THE PRESIDENT:—We will now have the second paper, by Professor Anthony, on Underwriters' Rules.

[The following paper was then read by the author.]