Portable Oscillograph

BY J. W. LEGG

Westinghouse Electric & Mfg. Co.

INTRODUCTION

THE use of the oscillograph for recording the instantaneous values of electrical phenomena has steadily increased in both scholastic and commercial institutions. Formerly it was seldom necessary to use the oscillograph in the field. However, due to the increasing complexity in transmission circuits and in railway electrification problem, it has become more and more desirable to have a special, portable, commercial oscillograph which, besides having the properties of the best laboratory oscillograph shall also be extremely compact and light in weight.

This article describes such an oscillograph which, furthermore, is permanently assembled in two units, which have been taken by the engineer into a Pullman to the place of test, and set up, ready for use in half an hour's time. There are many novel features in this oscillograph which make it independent of a direct-current supply, and which makes its adjustments more permanent, its operation more simple, and its results more reliable than heretofore possible with other forms of oscillographs.

THE OSCILLOGRAPH AND ITS GALVANOMETER

An oscillograph consists essentially of an optical system for throwing a beam of light onto the vibrating mirror of the galvanometer which mirror in turn reflects this beam of light onto a photographic film, passing at right angles to the vibrating beam, some distance from the galvanometer. This makes a *current-time* record, on the film; in which *distance* along the film is proportional to *time*, and *deflection* (of the beam of light) is proportional to the *instantaneous* value of *current* passing through the galvanometer vibrator.

Several standard makes of the moving coil oscillograph galvanometer were considered when the writer first planned a more portable commercial oscillograph. The permanent magnet type was light in weight but did not have a short enough natural period of oscillation to act properly on very fast transients or to respond to the high harmonics in some alternating current waves. The best standard electromagnet types of oscillograph galvanometer were superior in characteristics of natural period and sensitivity but were bulky and required a supply of direct current (usually 110 volts). Both of these drawbacks were serious for a portable commercial oscillograph, and hence an entirely new galvanometer and accompanying apparatus were designed to fulfill the more exacting requirements.

SURMOUNTING FORMER DIFFICULTIES

This oscillograph was designed to be independent of direct-current supply, for it is often desirable to make oscillograph records in a power-house, substation, fac-

tory, etc., where there is either no direct-current supply or where the supply is unreliable, due to sudden voltage changes. Former oscillograph apparatus which used d-c. for the galvanometer fields, arc lamp, electrically operated shutter, etc., required a two-kw. motor-generator set, or a large storage battery (which had to be kept charged) when no suitable d-c. supply was already available. Such was usually larger and much heavier than all of the other oscillograph apparatus combined.

As alternating current is in much more general use, for lighting and for power, the light source and the film motor were designed to operate on a-c. An incandescent lamp was used (with special means to give the filament great intrinsic brilliancy), the photographic shutter was designed to operate mechanically, and the galvanometer field circuit to operate on ten watts, supplied by a small storage battery, all being enclosed in the oscillograph case. This case also contains the low and high resistances, for each of the three galvanometer elements, in order that they may be used for any potential up to several thousand volts.

The lamp and the film motor are operated from a small transformer which may be plugged into any ordinary lamp socket or power supply of approximately 110 or 220 volts at any frequency from 20 to 70 cycles. Thus this portable apparatus requires, momentarily, less than 300 watts, a-c., instead of 2000 watts, d-c. (as was formerly required).

If a test is to be made where there is no alternating current supply, the gas filled incandescent lamp may be readily removed and an external d-c. arc lamp substituted. Also a d-c. motor can be used in place of the induction motor, for driving the photographic film. In practise it has been found that alternating current is almost always available, while proper direct current is seldom available outside of the laboratory.

A general view of the portable oscillograph is shown in Fig. 1. The main oscillograph case is shown to the left. This is 14 inches high, 13 inches wide, and 25 inches long over all. It contains the lamp house, shown at extreme left, the galvanometer, in the rear upper part of the case, the optical box, to which the photographic drum is attached, the ammeter and control switches, the element resistances with their control panel and the storage battery.

To the right is shown the motor board, on which are mounted: the induction motor with helical gears, for driving the photographic drum at desired speed, the transformer, and the control panel, with switches, fuses and lamp rheostat.

These two units together weigh but 135 pounds including side covers and carrying arrangement. They

take the place of former apparatus which weighed (ready for shipment) *from one-half to two tons* (depending whether or not suitable 110-volt direct current was available at the place of test).

The *galvanometer* is shown in Fig. 2. This instrument is 7 inches square, at the base, and $4\frac{1}{4}$ inches high over all. There are three separate elements, each insulated for over 10,000 volts from its neighbor. The most novel feature is the electromagnetic series

FIG. 1—PORTABLE OSCILLOGRAPH IN TWO UNITS

field circuit. There is but a *single* exciting coil which forces the magnetic flux in a *series path* through the three elements. There are three effective gaps in the iron circuit, one for each element, and four *insulating gaps*. The effective gaps are small in cross-section so as to concentrate the magnetic flux about each vibrating element. The insulating gaps are of micarta and are large in cross-section so as to have the least possible reluctance and still present sufficient insulation between the elements. This design is so efficient that

FIG. 2—THREE-ELEMENT GALVANOMETER SERIES MAGNETIC CIRCUIT

it requires but 10 watts, applied to the field coil to nearly saturate the element pole tips, thus giving as strong a magnetic field as is practical.

One *vibrator element* is shown to one side, the other two elements are in place in their wells. These wells contain the damping fluid which prevents over-travel of the vibrating mirrors. They are closed by the element tops so as to be both dust and oil tight. This feature is quite important for a portable oscillograph. The very fine ribbon of metal, which forms the moving

coil of the galvanometer, is entirely immersed in oil. A low resistance of the same material, is mounted in air so that it will clear the circuit, when an excessive current passes, and thus save the element.

As is the case with most *moving coil oscillograph galvanometers*, the coil actually consists of a single turn of very fine conductor, supported by two ivory bridges so that the effective part of the coil is essentially two parallel wires with the current passing down one wire and up the other. The motoring action of the conductors, carrying a current at right angles to the lines of force of the magnetic field, tends to force one wire forward and the other backward, in proportion to the current passing through them. These parallel conductors are kept taut by a tension spring which transmits its force to the loop through a lever and a tiny ivory pulley. The lever is *balanced* so that any shock will not tend to break the fine conductor. A very small mirror bridges the parallel conductors at the center of the magnetic gap. This reflects the beam of light to the photographic film. With this optical advantage

FIG. 3—PANEL SIDE OF OSCILLOGRAPH CASE

the deflection is approximately one inch to 0.12 ampere. Any element may be used across a shunt, as a millivoltmeter, to record instantaneous current, or, with a series resistance, to record instantaneous values of voltage.

Fig. 3 shows the front and the element resistance *panel side of the oscillograph*. There are three similar sets of switches and binding posts, one set for each element. Each set consists of two dial resistances, one with a range from 0 to 100 ohms and the other from 100 to 10,000 ohms. The double-pole, double-throw knife switch places the element, and its fine fuse, in series with either the high-resistance or the low-resistance dial. There are four binding posts per element. The two closer together are in the low resistance circuit, for use with e.m.f.s. below 10 volts, or for connection across a current shunt. The other two posts have a greater spacing to indicate that they are to be used for higher voltages, with the higher resistance. With this connection the element can be used to record the instantaneous values of e.m.f. up to about 4000 volts, d-c., or about 1500 volts, a-c. In every case the resistance is nearest the left hand

terminal so that when high voltage is used the right hand terminal can be kept in the side of the line nearest the ground, thus keeping the element on the ground side. If more than 10,000 ohms is desired, in one element circuit, one of the other high resistances can be connected into circuit.

This whole panel, with all the resistance units, can be removed from the oscillograph for inspection or repair. The resistances are wound on thin micarta cards, so as to be as non-inductive as possible. They are located behind the panel, underneath the galvanometer compartment.

The adjusting screw for the incandescent lamp is shown below the smoked glass window and above the battery charging terminals.

A fine wire screen between the element resistance panel and the galvanometer partition, allows ventilation of the element resistances.

FIG. 4—BATTERY COMPARTMENT SIDE OF OSCILLOGRAPH

One of the *snap switches*, in front, connects the ammeter to indicate either the galvanometer field current or the battery charging current. The normal field current is $2\frac{1}{4}$ amperes. The conveniently located switch, above the ammeter, is in the field circuit and is used to conserve the battery current when no charging current is at hand. The variable resistances are in the battery and galvanometer field circuits.

Fig. 4 shows the *battery compartment side of the oscillograph*. The common cover to the galvanometer compartment and optical box is shown in its raised position. The top of the galvanometer can be seen at the rear. Below this is the element resistance compartment with 30,000 ohms of non-inductive resistances. The three longitudinal ventilating slots can be seen at the side. There are nine similar slots in the base, to allow cool air to enter below the resistances.

The *storage battery* is shown half withdrawn from its compartment. Above is shown the rectangular plate with the three-point plug receptacle, used in connecting

the incandescent lamp and trip magnet mechanism to the low-voltage side of the transformer. The trip magnet is shown on the side of the optical box, in a recess near the film pulley.

Fig. 5 is a detailed view of the trip magnet, remote-control switch, photographic shutter release, lamp-extinguishing switch etc. These are all novel features and all add greatly to the efficiency and simplicity of operation of the oscillograph.

As mentioned before, the *shutter is mechanically operated* and is of the semi focal-plane type. This is

FIG. 5—SHUTTER TRIP AND REMOTE CONTROL MECHANISM

so arranged as to permit the reflected beams from the tiny vibrating mirrors to strike the film for just one complete revolution. Also the start of the exposure always comes very near the beginning of the rectangular film. *With this arrangement no important transient could ever occur just at the overexposing of the film.*

The *shutter* is essentially a hollow cylinder with a longitudinal slot on each side. When these slots line up, horizontally, the shutter is open. The cylindrical condensing lens lies just between the shutter and the film holder.

FIG. 6—DRIVING HEAD

The *shutter operating device* is in two main parts. The radial fingers and hub, on the shutter shaft, receive a torsional force from the spiral spring. The release arm is actuated, through a connecting rod, by a crank pin on the film pulley shaft. When all is ready for the phenomena to be recorded on the photographic film, the trip magnet releases the longer of the two radial fingers; this allows the shorter finger to rest on the release arm. When the arm almost reaches its extreme travel, away from the shutter, the short arm drops, due to the torsional force exerted by the

spiral spring, the longer finger is stopped by the arm, thus holding the shutter open. As the arm returns it forces the longer finger into the hub, and as it moves outward again a flat spring holds this finger in, so that it is now just the same length as the first finger. When the arm reaches its outward position again the second finger drops and the shutter closes, after allowing just one revolution exposure on the revolving film.

The instant the *trip magnet* is excited it releases the remote control switch, but the shutter does not open until the overlapped end of the film is presented towards the galvanometer. A contact on the film pulley shaft,

FIG. 7—OPTICAL BOX

may be set so as to trip the magnet at any interval of time, ahead of the exposure, equal to the time lag of the remote controlled apparatus (circuit breaker, switch, relay, fuses, etc.) being studied. Thus, if the operator desires, he can cause the transient phenomena to occur within 0.01 sec. after the beginning of the exposure. This is of *great value for commercial work*, where many fast transient conditions must be recorded.

Fig. 7 shows the *optical box* on its face with the under side nearest the observer. This is made of aluminum so as to be as light in weight as possible. The trip magnet, shutter fingers, observation door, etc., can be seen to the left. The condensing lens is adjustable and can be twisted to one side when an external arc lamp is to be used. There are four reflecting prisms and slots, one set for each element, and one for a stationary beam or for a timing line device. All of these are very conveniently adjusted from above, their knurled heads being in plain view when the main cover is raised. Furthermore, when using the incandescent lamp, these various items need to be adjusted but once, and then *any number of oscillograms may be taken without further adjustment*, until renewal of the lamp.

Fig. 8 shows a close up view of the *motor board*. The rheostat switch on the panel, is in the lamp circuit, which is supplied from the low-voltage secondary of the transformer. The first contact closes the lamp circuit through sufficient resistance to give normal

voltage to the lamp. This *lamp* is of the low-voltage, high-current type with an extremely concentrated filament. The central part of this filament is arranged to have maximum intrinsic brilliancy, its normal brightness being increased by the light from the surrounding coil of the filament. Intrinsic brilliancy, and not total candle power, is of prime importance, for only a projected area of about 20 miles square can be used to any advantage.

The second contact position, on the *lamp control switch*, increases the voltage, applied to the lamp, by about 12 per cent, the third by 30 per cent, and the fourth by 60 per cent. The lamp would burn continuously, many hours, on 112 per cent voltage, but would have a short life at 130 per cent volts. At 160 per cent voltage, filament life would be less than one second. For this reason an automatic *lamp extinguishing switch* is used. This is located between the trip magnet core and the optical box. The closing of the shutter snaps open this special switch. The lamp cannot be lighted except when the shutter is set. A special combination stop and contact is provided, under the lamp control switch arm, so that the instant the desired abnormal voltage is applied, to the lamp, the trip magnet operates the remote-control switch, the shutter opens, the oscillograph record is made, the shutter closes, and in so doing opens the lamp extinguishing switch, thus saving the lamp. With this arrangement hundreds, and possibly thousands of films may be taken before the lamp burns out. The value of the abnormal voltage chosen depends on the speed of the film, for high-speed films require much greater intrinsic brilliancy than low-speed films.

FIG. 8—MOTOR BOARD, WITH TRANSFORMER AND CONTROL SWITCHES

Note that the lamp is thus at the greatest abnormal voltage for the shortest period of time, and at a moderate voltage for a longer period of time. The abnormal voltage increases the intrinsic brilliancy *many times*, thus enabling one to take oscillograms, with this incandescent lamp, which otherwise would require a direct current arc lamp consuming ten to twenty times as many watts. For some very special work, where the film speed must be greater than about 100 inches per second, it becomes necessary to use a direct-current arc. This can be applied to this oscillograph

in a few moments time, when direct current is available. If great accuracy is required in *recurrent phenomena* (such as in determining wave forms) it would be much better to use the *synchronous polar film*¹ with the incandescent lamp, than to try to get a large scale wave on the rectangular film.

The double-pole double-throw transformer switch places the two primary coils in series or in parallel; the former for 220-volt, and the latter for 110-volt supply. The single-pole switch throws the induction motor on 110 or 55 volts, for 60 or for 25-cycle supply. Actually the motor will run on any frequency from 20 to 70 cycles.

The four steps in the *pulleys*, together with the *helical gears*, give an ideal range of speed reductions. When the motor pulley is pushed in, a clutch engages with the motor shaft and gives direct drive. When this pulley is pulled out it is driven, through the back gearing, at one sixteenth motor speed. The four steps, for the round belt, are so arranged that the center distances are the same, for the four belt positions.

FIG. 9—VARIABLE SHUNT

Provided the induction motor supply does not vary in frequency the film speed remains the same for any one belt position, within a fraction of one per cent. This is a great advantage, for *no timing wave is needed*, on any film, after the film speed has once been determined, for that particular belt and gear position. Also, with this arrangement the number of cycles on a film, may be varied from about two to two hundred and forty. This is a greater range than is needed for any but a commercial oscillograph.

Fig. 9 shows the variable, non-inductive shunt which was designed to go with the portable commercial oscillograph. It consists of five manganin strips with special arrangement for connecting any number of them in series or in parallel. Furthermore their arrangement makes them very nearly non-inductive. When the five strips are all in series the resistance drop is great enough to give a good deflection, on the above oscillograph, with a shunt current of 10 or 20 amperes. With the strips all in parallel, approximately the same deflection would be produced by

500 amperes as was produced by 20 amperes in the series position. The shunt will carry about one thousand amperes continuously and can be used for momentary currents of 50,000 amperes.

The heavy terminals, to the left, receive the power conductors. The arrangement for connecting the strips either in series or in parallel is very convenient. Two heavy brass screws are connected to each end of each of the five strips. One from the right hand side of each strip passes through one bus bar, but is insulated therefrom; and one from the left hand side of each strip passes through the other bus bar, likewise. As the wing nuts are turned down, on these screws of any one strip, that strip is placed across the bus bars. A set of four diagonal conductors, screws and wing nuts make it possible to connect any number of the strips in series. One series-parallel arrangement is also possible. If the drop across the shunt makes too great a deflection, when the element is connected straight across it, series resistance is added in the element circuit by means of the upper dial switch shown in Fig. 3. The resistance of the strips was so chosen that 50 amperes direct current through one strip, gives a deflection of once inch, with no series resistance added to the element circuit. With five ohms, series resistance, added to the element circuit it takes 300 amperes to give one inch deflection. In general the following formula holds, approximately.

Where A = current in amperes D = deflection on film in inches.

P = number of strips in parallel S = number in series.

R = external resistance in element circuit, in ohms.

50 = amperes in one strip to give one inch deflection on film with no external resistance in element circuit.

Then $A = 50D (1 + R) P/S$ or, sensitivity = amperes per inch = $50 (1 + R) P/S$.

Except for approximate work any oscillograph should be calibrated by passing a steady value of direct current through the particular shunt being used with the same resistance in series with the element as was used in the important test. If this requires a very large current (to give the proper deflection) the true calibration could be figured from the results of a calibration obtained with a much lower current passing through a much higher resistance shunt; the currents required to give the same deflection being inversely proportional to the shunt resistances. Thus, 200 amperes passing through the five strips in series would give approximately the same deflection, on the film, as 5000 amperes flowing through the five strips in parallel. When the exact ratio of resistances is known this can be figured quite accurately.

This one shunt is suitable for a *very great range* of

1. L. W. Chubb, *Electrical Journal*, May 1914.

work, and yet can be carried in a space 10 by 10 by 8 in. Naturally, however, it cannot be extremely light in weight and still be suitable for even a momentary current of 50,000 amperes.

For heavy alternating currents it is advisable to use current transformers with five ampere shunts in the secondary circuit, as is the general practise.

The shutter mechanism construction makes it possible to use a special film holder having a long film, in a magazine, on which several exposures can be taken without reloading, and without the help of a dark room. It would be impossible to use such a film for transients unless the oscillograph shutter mechanism caused the exposure to begin at the same part of the revolving drum, each time, as is the case with this instrument.

The operator can make all oscillograph adjustments and all connections with the apparatus to be tested, at his leisure; then when all is ready he has but to *depress the control switch and everything works automatically*. In fact, the operator could be miles away from the oscillograph, and by the pressure of a single button the whole apparatus could be made to function perfectly.

This oscillograph has been used to operate, successively, a closing switch, which caused an abnormal current to build up through an inductance, then to trip a circuit breaker and operate the polar, multi-exposure, high-speed camera² so that the latter would make a series of photographs of the rapidly extinguished arc, while the oscillograph made a complete record of the building up and rupture of the current, and the accompanying voltage surges.

² J. W. Legg, *Electric Journal*, December, 1919

SUMMARY OF THE SPECIAL FEATURES OF THE PORTABLE COMMERCIAL OSCILLOGRAPH

1. Special compactness of apparatus, including the series electromagnet galvanometer.
2. Use of an incandescent lamp with special arrangements to obtain very great intrinsic brilliancy.
3. Mechanically operated focal plane shutter, which always starts exposures at the beginning of the film.
4. Remote-control switch to cause transient to appear at any desired part of the film.
5. Trip magnet to operate remote-control switch and shutter immediately after abnormal voltage is applied to the incandescent lamp.
6. Lamp extinguishing switch to prevent the filament from being destroyed.
7. Self-contained storage battery to supply galvanometer field.
8. Switch for placing ammeter in galvanometer field or battery charging circuits.
9. Element resistances and control panel for commercial voltages.
10. All the above apparatus mounted in a single case 13 by 14 by 25 inches over all, and weighing but 82 pounds.
11. Transformer, for 110 or 220 volts, 20 to 70 cycles, supply for incandescent lamp, trip magnet, and induction motor operation.
12. Switches for motor, transformer and lamp control.
13. Induction motor with back gear and step pulley arrangement for driving photographic drum at uniform speed over a great range of speeds.
14. This *portable commercial oscillograph* arranged in but two units which together weigh but 135 pounds, including storage battery and transformer.

THE ELECTRIFICATION OF STEAM RAILROADS

One of the most important subjects to come before the recent N. E. L. A. Convention was "The Electrification of Steam Railroads," and the report of the Committee was submitted at the third general session, Friday, May 21, by Mr. Frank M. Kerr, of the Montana Power Company, of Butte, Montana, who is Chairman of the Committee. An abstract of Mr. Kerr's elaborate study on the subject is as follows:

"If all the steam railroads in the country were electrified with power furnished from large steam-generating electric stations, the total fuel required would be equivalent to 53,500,000 tons of coal, as against the actual figure for railroad coal used during the year 1918, of 175,000,000 tons. Thus, by electrification of the railroads, 122,500,000 tons of coal would have been saved.

"The Chicago, Milwaukee & St. Paul Railway and the Montana Power Company have demonstrated in Montana the entire practicability and great superiority of electric power for the operation of a heavy trunk-line

railway, by more than four years of 100 per cent operation. Four-thousand-ton trains go up and down heavy mountain grades under perfect control, at speeds never known before and with a regularity which is phenomenal."

"The change from steam to electric operation means more than a mere change in type of locomotive used. It means a change in the entire conception of the art of railroad transportation."

"In short, by adopting electrification, the railroad company is relieved entirely of the business of generating power, and is enabled to concentrate on its main business of transportation." * * *

"The higher speed at which cars can be hauled over a road with electric operation allows the same amount of freight to be handled with a considerably smaller number of cars. This is such an important item that it is safe to say that if all the roads in the country were electrically operated at the present time there would be no car shortage."—*N. E. L. A. Bulletin*.